

# Branch Circuit Protection for ABB drives

## Acceptable fuses, manual motor protectors and circuit breakers

### **Purpose**

This document outlines alternative fuses, manual motor protectors and circuit breakers that can be used for branch circuit protection on ABB drives.

### **How to use this information**

The specific drive's hardware manual includes fuse and sometimes circuit breaker recommendations for the drive. In addition to the branch circuit protection identified in the manuals, alternative fuses and circuit breakers can be used if they meet certain characteristics. The guidelines in this document describe which fuses, manual motor protectors and circuit breakers are acceptable alternatives.

# Table of Contents

<b>ACS380 drives.....</b>	<b>3</b>
Fuse Information	3
ACS380-04, 200...240 V 1-phase fuses .....	4
ACS380-04, 200...240 V fuses.....	5
ACS380-04, 380...480 V fuses .....	6
Manual Motor Protector Information	7
ACS380-04, 200...240 V 1-phase manual motor protectors .....	7
ACS380-04, 200...240 V manual motor protectors.....	7
ACS380-04, 380...480 V manual motor protectors .....	7
<b>— ACH, ACQ, ACS580 drives.....</b>	<b>9</b>
Fuse Information	9
ACH, ACQ, ACS580-01, 208/230 V fuses .....	11
ACH, ACQ, ACS580-01, 480 V fuses .....	12
ACH, ACQ, ACS580-01, 575 V fuses .....	13
ACH, ACQ580-04, 480 V fuses .....	14
ACH, ACQ580-31, 480 V fuses .....	15
ACH, ACQ580-34, 480 V fuses .....	15
Circuit Breaker Information	16
ACH, ACQ, ACS580-01, 230 V circuit breakers .....	17
ACH, ACQ, ACS580-01, 480 V circuit breakers .....	17
<b>— ACS880 drives.....</b>	<b>18</b>
Fuse Information	18
ACS880-01, 230 V fuses .....	20
ACS880-01, 480 V fuses .....	21
ACS880-01, 575 V fuses .....	22
ACS880-04, 480 V fuses .....	23
ACS880-04, 575 V fuses .....	24
ACS880-04XT, 480 V fuses .....	25
ACS880-04XT, 575 V fuses .....	25
ACS880-04F, 575 V fuses .....	27
ACS880-04FXT, 480 V fuses .....	28
ACS880-04FXT, 575 V fuses .....	28
ACS880-11, -31, 480 V fuses.....	29
ACS880-14, -34, 480 V fuses .....	30
ACS880-14, -34, 575 V fuses .....	30
Circuit Breaker Information	31
ACS880-01, 480 V circuit breakers .....	31

# ACS380 drives

## Purpose

This section outlines alternative branch circuit protection that may be used with ACS380-04 base drives R0 through R4 frame size.

## How to use this information

The drive hardware manual includes recommendations suitable branch circuit protection for the drives. In addition to the protection identified in the manual, alternative protective devices can be used if they meet certain characteristics. The guidelines in this document describe which protective devices are acceptable alternatives. This document is a supplement to the following drive hardware manuals:

- 3AXD50000029274 ACS380-04 drives

## Fuse Information

ACS380-04 drives are suitable for use on a circuit capable of delivering not more than 100 kA symmetrical amperes (RMS) at 240 and 480 V maximum, when protected by appropriate fuses.

The drives are tested in accordance with UL 61800-5-1 on a circuit having available system fault current of 100 kA maximum.

Hardware manuals for ACS380-04 drives recommend:

- Listed Class T (UL 248-15) fast acting fuses up to 100A.

ABB performed the fault testing with “umbrella fuses.” These fuses are calibrated to create worst case peak let-through current ( $I_{peak}$ ) and let-through energy ( $I^2t$ ) limits in accordance with the limits of the intended fuse class(es) and ratings. The umbrella fuse testing allows other listed fuses, which have let-through characteristics equal to or below these limits, to be used. Therefore, listed Class CC (UL 248-4) fuses (up to 30A) and listed (UL 248-8) Class J fast acting and high-speed fuses can also be used, since they provide equal or better protection. Likewise, listed (UL 248-17) fast acting cubed body (CF) fuses can be used as well.

In addition to the above guidelines, the following are additional rules that must be followed:

1. The UL listed fuses in the hardware manual tables, or the tables in this document, are the required branch circuit protection per NEC.
2. Fuses are required as part of the installation. Fuses are not included in the base drive configuration and must be provided by others.
3. Fuses with a higher current rating than specified must not be used.
4. Fuses with a lower current rating than specified may be used if they are of the same voltage and are UL 248 listed fast acting or high-speed fuses.
5. A fuse of a different class can be used at the high fault rating where the  $I_{peak}$  and  $I^2t$  of the new fuse is not greater than that of the specified fuse.
6. Recommended drive fuses must be used to maintain drive UL listing. Additional protection can be used. Refer to local codes and regulations.
7. When installing a drive always follow installation instructions and NEC requirements.
8. UL 248 listed, fast acting or high-speed fuses from other manufacturers can be used if they meet the rating requirements specified in the rules above.

Alternate recommended fuses for some of the major fuse manufacturers can be found in tables on the following pages. Other manufacturers not found on the tables below may be used if they meet the fuse requirements stated above.

**ACS380-04, 200...240 V 1-phase fuses**

Frame Size	200...240 V ACS380-04	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-15 Class T Fast Acting Fuses 300 V or 600 V				UL 248-8 Fast Acting Class J Fuses 600 V			
			Max Current	Voltage Rating	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison
			A	V								
R0	02A4-1	5.0	10	300 or 600	JJN-10 or JJS-10	JLLN010 or JLLS010	A3T10 or A6T10	TJN10 or TJS10	JKS-10	JLS10	A4J10	JFL10
R0	03A7-1	7.8	10	300 or 600	JJN-10 or JJS-10	JLLN010 or JLLS010	A3T10 or A6T10	TJN10 or TJS10	JKS-10	JLS10	A4J10	JFL10
R1	04A8-1	10.1	20	300 or 600	JJN-20 or JJS-20	JLLN020 or JLLS020	A3T20 or A6T20	TJN20 or TJS20	JKS-20	JLS20	A4J20	JFL20
R1	06A9-1	14.5	20	300 or 600	JJN-20 or JJS-20	JLLN020 or JLLS020	A3T20 or A6T20	TJN20 or TJS20	JKS-20	JLS20	A4J20	JFL20
R1	07A8-1	16.4	25	300 or 600	JJN-25 or JJS-25	JLLN025 or JLLS025	A3T25 or A6T25	TJN25 or TJS25	JKS-25	JLS25	A4J25	JFL25
R2	09A8-1	20.6	25	300 or 600	JJN-25 or JJS-25	JLLN025 or JLLS025	A3T25 or A6T25	TJN25 or TJS25	JKS-25	JLS25	A4J25	JFL25
R2	12A2-1	25.6	35	300 or 600	JJN-35 or JJS-35	JLLN035 or JLLS035	A3T35 or A6T35	TJN35 or TJS35	JKS-35	JLS35	A4J35	JFL35

Frame Size	200...240 V ACS380-04	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 High Speed Class J Fuses 600 V				UL 248-4 Class CC Fast Acting Fuses 600 V				UL 248-17 Class CF Fast Acting Cube Fuse 600 V
			Max Current	Voltage Rating	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison	Bussmann
			A	V									
R0	02A4-1	5.0	10	300 or 600	DFJ-10	LDFJ010	HSJ10	JHL10	KTK-R-10	KLKR10	ATMR10	HCLR10	FCF10RN
R0	03A7-1	7.8	10	300 or 600	DFJ-10	LDFJ010	HSJ10	JHL10	KTK-R-10	KLKR10	ATMR10	HCLR10	FCF10RN
R1	04A8-1	10.1	20	300 or 600	DFJ-20	LDFJ020	HSJ20	JHL20	KTK-R-20	KLKR20	ATMR20	HCLR20	FCF20RN
R1	06A9-1	14.5	20	300 or 600	DFJ-20	LDFJ020	HSJ20	JHL20	KTK-R-20	KLKR20	ATMR20	HCLR20	FCF20RN
R1	07A8-1	16.4	25	300 or 600	DFJ-25	LDFJ025	HSJ25	JHL25	KTK-R-25	KLKR25	ATMR25	HCLR25	FCF25RN
R2	09A8-1	20.6	25	300 or 600	DFJ-25	LDFJ025	HSJ25	JHL25	KTK-R-25	KLKR25	ATMR25	HCLR25	FCF25RN
R2	12A2-1	25.6	35	300 or 600	DFJ-35	LDFJ035	HSJ35	JHL35	-	-	-	-	FCF35RN

3AXD10001032874.xls Rev C

**ACS380-04, 200...240 V fuses**

Frame Size	200....240 V ACS380-04	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-15 Class T Fast Acting Fuses				UL 248-8 Fast Acting Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R1	02A4-2	3.6	6	600	JJS-6	JLLS006	A6T6	TJS6	JKS-6	JLS6	A4J6	JFL6
R1	03A7-2	5.6	10	600	JJS-10	JLLS010	A6T10	TJS10	JKS-10	JLS10	A4J10	JFL10
R1	04A8-2	7.2	10	600	JJS-10	JLLS010	A6T10	TJS10	JKS-10	JLS10	A4J10	JFL10
R1	06A9-2	10.4	20	600	JJS-20	JLLS020	A6T20	TJS20	JKS-20	JLS20	A4J20	JFL20
R1	07A8-2	11.7	20	600	JJS-20	JLLS020	A6T20	TJS20	JKS-20	JLS20	A4J20	JFL20
R1	09A8-2	14.7	20	600	JJS-20	JLLS020	A6T20	TJS20	JKS-20	JLS20	A4J20	JFL20
R2	12A2-2	18.3	25	600	JJS-25	JLLS025	A6T25	TJS25	JKS-25	JLS25	A4J25	JFL25
R3	17A5-2	24.6	35	600	JJS-35	JLLS035	A6T35	TJS35	JKS-35	JLS35	A4J35	JFL35
R3	25A0-2	35.1	40	600	JJS-40	JLLS040	A6T40	TJS40	JKS-40	JLS40	A4J40	JFL40
R4	032A-2	45.0	60	600	JJS-60	JLLS060	A6T60	TJS60	JKS-60	JLS60	A4J60	JFL60
R4	048A-2	57.6	100	600	JJS-100	JLLS100	A6T100	TJS100	JKS-100	JLS100	A4J100	JFL100
R4	055A-2	60.0	100	600	JJS-100	JLLS100	A6T100	TJS100	JKS-100	JLS100	A4J100	JFL100

Frame Size	200....240 V ACS380-04	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 High Speed Class J Fuses				UL 248-4 Class CC Fast Acting Fuses				UL 248-17 Class CF Fast Acting Cube Fuse
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann
			A	V									
R1	02A4-2	3.6	6	600	DFJ-6	LDFJ006	HSJ6	JHL6	KTK-R-6	KLKR6	ATMR6	HCLR6	FCF6RN
R1	03A7-2	5.6	10	600	DFJ-10	LDFJ010	HSJ10	JHL10	KTK-R-10	KLKR10	ATMR10	HCLR10	FCF10RN
R1	04A8-2	7.2	10	600	DFJ-10	LDFJ010	HSJ10	JHL10	KTK-R-10	KLKR10	ATMR10	HCLR10	FCF10RN
R1	06A9-2	10.4	20	600	DFJ-20	LDFJ020	HSJ20	JHL20	KTK-R-20	KLKR20	ATMR20	HCLR20	FCF20RN
R1	07A8-2	11.7	20	600	DFJ-20	LDFJ020	HSJ20	JHL20	KTK-R-20	KLKR20	ATMR20	HCLR20	FCF20RN
R1	09A8-2	14.7	20	600	DFJ-20	LDFJ020	HSJ20	JHL20	KTK-R-20	KLKR20	ATMR20	HCLR20	FCF20RN
R2	12A2-2	18.3	25	600	DFJ-25	LDFJ025	HSJ25	JHL25	KTK-R-25	KLKR25	ATMR25	HCLR25	FCF25RN
R3	17A5-2	24.6	35	600	DFJ-35	LDFJ035	HSJ35	JHL35	-	-	-	-	FCF35RN
R3	25A0-2	35.1	40	600	DFJ-40	LDFJ040	HSJ40	JHL40	-	-	-	-	FCF40RN
R4	032A-2	45.0	60	600	DFJ-60	LDFJ060	HSJ60	JHL60	-	-	-	-	FCF60RN
R4	048A-2	57.6	100	600	DFJ-100	LDFJ100	HSJ100	JHL100	-	-	-	-	FCF100RN
R4	055A-2	60.0	100	600	DFJ-100	LDFJ100	HSJ100	JHL100	-	-	-	-	FCF100RN

3AXD10001032874.xls Rev C

**ACS380-04, 380...480 V fuses**

Frame Size	380....480 V ACS380-04	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-15 Class T Fast Acting Fuses				UL 248-8 Fast Acting Class J Fuses			
			Max Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R0	01A8-4	2.9 / 2.6	6	600	JJS-6	JLLS006	A6T6	TJS6	JKS-6	JLS6	A4J6	JFL6
R1	02A6-4	4.2 / 3.4	6	600	JJS-6	JLLS006	A6T6	TJS6	JKS-6	JLS6	A4J6	JFL6
R1	03A3-4	5.3 / 4.8	6	600	JJS-6	JLLS006	A6T6	TJS6	JKS-6	JLS6	A4J6	JFL6
R1	04A0-4	6.4 / 5.4	10	600	JJS-10	JLLS010	A6T10	TJS10	JKS-10	JLS10	A4J10	JFL10
R1	05A6-4	9.0 / 7.7	10	600	JJS-10	JLLS010	A6T10	TJS10	JKS-10	JLS10	A4J10	JFL10
R1	07A2-4	11.5 / 9.6	20	600	JJS-20	JLLS020	A6T20	TJS20	JKS-20	JLS20	A4J20	JFL20
R1	09A4-4	15.0 / 12.2	20	600	JJS-20	JLLS020	A6T20	TJS20	JKS-20	JLS20	A4J20	JFL20
R2	12A6-4	20.2 / 17.6	25	600	JJS-25	JLLS025	A6T25	TJS25	JKS-25	JLS25	A4J25	JFL25
R3	17A0-4	27.2 / 22.4	35	600	JJS-35	JLLS035	A6T35	TJS35	JKS-35	JLS35	A4J35	JFL35
R3	25A0-4	40.0 / 33.6	40	600	JJS-40	JLLS040	A6T40	TJS40	JKS-40	JLS40	A4J40	JFL40
R4	032A-4	45.0 / 37.9	60	600	JJS-60	JLLS060	A6T60	TJS60	JKS-60	JLS60	A4J60	JFL60
R4	038A-4	50.0 / 44.7	80	600	JJS-80	JLLS080	A6T80	TJS80	JKS-80	JLS80	A4J80	JFL80
R4	045A-4	56.0 / 49.8	100	600	JJS-100	JLLS100	A6T100	TJS100	JKS-100	JLS100	A4J100	JFL100
R4	050A-4	60.0 / 50.4	100	600	JJS-100	JLLS100	A6T100	TJS100	JKS-100	JLS100	A4J100	JFL100

Frame Size	380....480 V ACS380-04	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 High Speed Class J Fuses				UL 248-4 Class CC Fast Acting Fuses				UL 248-17 Class CF Fast Acting Cube Fuse
			Max Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann
			A	V									
R0	01A8-4	2.9 / 2.6	6	600	DFJ-6	LDFJ006	HSJ6	JHL6	KTK-R-6	KLKR6	ATMR6	HCLR6	FCF6RN
R1	02A6-4	4.2 / 3.4	6	600	DFJ-6	LDFJ006	HSJ6	JHL6	KTK-R-6	KLKR6	ATMR6	HCLR6	FCF6RN
R1	03A3-4	5.3 / 4.8	6	600	DFJ-6	LDFJ006	HSJ6	JHL6	KTK-R-6	KLKR6	ATMR6	HCLR6	FCF6RN
R1	04A0-4	6.4 / 5.4	10	600	DFJ-10	LDFJ010	HSJ10	JHL10	KTK-R-10	KLKR10	ATMR10	HCLR10	FCF10RN
R1	05A6-4	9.0 / 7.7	10	600	DFJ-10	LDFJ010	HSJ10	JHL10	KTK-R-10	KLKR10	ATMR10	HCLR10	FCF10RN
R1	07A2-4	11.5 / 9.6	20	600	DFJ-20	LDFJ020	HSJ20	JHL20	KTK-R-20	KLKR20	ATMR20	HCLR20	FCF20RN
R1	09A4-4	15.0 / 12.2	20	600	DFJ-20	LDFJ020	HSJ20	JHL20	KTK-R-20	KLKR20	ATMR20	HCLR20	FCF20RN
R2	12A6-4	20.2 / 17.6	25	600	DFJ-25	LDFJ025	HSJ25	JHL25	KTK-R-25	KLKR25	ATMR25	HCLR25	FCF25RN
R3	17A0-4	27.2 / 22.4	35	600	DFJ-35	LDFJ035	HSJ35	JHL35	-	-	-	-	FCF35RN
R3	25A0-4	40.0 / 33.6	40	600	DFJ-40	LDFJ040	HSJ40	JHL40	-	-	-	-	FCF40RN
R4	032A-4	45.0 / 37.9	60	600	DFJ-60	LDFJ060	HSJ60	JHL60	-	-	-	-	FCF60RN
R4	038A-4	50.0 / 44.7	80	600	DFJ-80	LDFJ080	HSJ80	JHL80	-	-	-	-	FCF80RN
R4	045A-4	56.0 / 49.8	100	600	DFJ-100	LDFJ100	HSJ100	JHL100	-	-	-	-	FCF100RN
R4	050A-4	60.0 / 50.4	100	600	DFJ-100	LDFJ100	HSJ100	JHL100	-	-	-	-	FCF100RN

3AXD10001032874.xls Rev C

## Manual Motor Protector Information

ABB UL file E211945 Volume 15, Section 1 lists the ABB Type E manual motor protectors MS132 & S1-M3-25 and MS165 as an alternative to UL classified fuses as a means of branch circuit protection. This is in accordance with the National Electrical Code (NEC). When the correct ABB Type E manual motor protector is selected from the table and used for branch circuit protection the drive is suitable for use in a circuit capable of delivering not more than 65 kA RMS symmetrical amperes at the drive maximum rated voltage. See the following table for the ACS380 drive and MMP combinations listed below.

**Combinations of Type E MMP's and drives installed with UL Type 1 kits are NOT included in the listing.** Drive & MMP combinations must be assembled in an enclosure conforming to minimum enclosure volume.

### ACS380-04, 200...240 V 1-phase manual motor protectors

Frame Size	200...240 V ACS380-04	Input Amps	MMP Nominal Current (A)	MMP Voltage	Enclosure Minimum Volume (in <sup>3</sup> ) <sup>5</sup>	MMP Type E <sup>1,2</sup>
R0	02A4-1	5.0	6.3	600	1850	MS132-6.3 & S1-M3-25 <sup>3</sup>
R0	03A7-1	7.8	10	600	1850	MS132-10 & S1-M3-25 <sup>3</sup>
R1	04A8-1	10.1	16	600	1850	MS165-16
R1	06A9-1	14.5	16	600	1850	MS165-16
R1	07A8-1	16.4	20	600	1850	MS165-20
R2	09A8-1	20.6	25	600	1850	MS165-25
R2	12A2-1	25.6	32	600	1850	MS165-32

### ACS380-04, 200...240 V manual motor protectors

Frame Size	200...240 V ACS380-040	Input Amps	MMP Nominal Current (A)	MMP Voltage	Enclosure Minimum Volume (in <sup>3</sup> ) <sup>5</sup>	MMP Type E <sup>1,2</sup>
R1	02A4-2	3.6	9.6	600	1850	MS132-6.3 & S1-M3-25 <sup>3</sup>
R1	03A7-2	5.6	10	600	1850	MS132-10 & S1-M3-25 <sup>3</sup>
R1	04A8-2	7.2	10	600	1850	MS132-10 & S1-M3-25 <sup>3</sup>
R1	06A9-2	10.4	16	600	1850	MS165-16
R1	07A8-2	11.7	16	600	1850	MS165-16
R1	09A8-2	14.7	20	600	1850	MS165-20
R2	12A2-2	18.3	25	600	1850	MS165-25
R3	17A5-2	24.6	32	600	1850	MS165-32
R3	25A0-2	35.1	42	600	1850	MS165-42
R4	032A-2	45.0	54	600	4577	MS165-54
R4	048A-2	57.6	80	600	4577	MS165-80
R4	055A-2	60.0	80	600	4577	MS165-80

### ACS380-04, 380...480 V manual motor protectors

Frame Size	380...480 V <sup>4</sup> ACS380-040	Input Amps	MMP Nominal Current (A)	MMP Voltage	Enclosure Minimum Volume (in <sup>3</sup> ) <sup>5</sup>	MMP Type E <sup>1,2</sup>
R0	01A8-4	2.9 / 2.6	4	600	1850	MS132-4.0 & S1-M3-25 <sup>3</sup>
R1	02A6-4	4.2 / 3.4	6.3	600	1850	MS132-6.3 & S1-M3-25 <sup>3</sup>
R1	03A3-4	5.3 / 4.8	6.3	600	1850	MS132-6.3 & S1-M3-25 <sup>3</sup>
R1	04A0-4	6.4 / 5.4	10	600	1850	MS132-10 & S1-M3-25 <sup>3</sup>
R1	05A6-4	9.0 / 7.7	10	600	1850	MS132-10 & S1-M3-25 <sup>3</sup>
R1	07A2-4	11.5 / 9.6	16	600	1850	MS165-16
R1	09A4-4	15.0 / 12.2	16	600	1850	MS165-16
R2	12A6-4	20.2 / 17.6	20	600	1850	MS165-20
R3	17A0-4	27.2 / 22.4	32	600	1850	MS165-32
R3	25A0-4	40.0 / 33.6	42	600	1850	MS165-42
R4	032A-4	45.0 / 37.9	54	600	4577	MS165-54
R4	038A-4	50.0 / 44.7	65	600	4577	MS165-65
R4	045A-4	56.0 / 49.8	73	600	4577	MS165-73
R4	050A-4	60.0 / 50.4	80	600	4577	MS165-80

3AXD10001032874.xls Rev C

1. All manual motor protectors listed are Type E self-protected up to 65 kA. See ABB publication 2CDC131060M0202 - Manual Motor Starters Guide for complete technical data on the ABB Type E manual motor protectors. For these manual motor protectors to be used for branch circuit protection, they must be UL listed Type E manual motor protectors, otherwise they can be used only as an At Motor Disconnect. "At Motor Disconnect" is a disconnect just ahead of the motor on the load side of the panel.
2. Manual motor protectors may require adjusting the trip limit from the factory setting at or above the drive input Amps to avoid nuisance tripping. If the manual motor protector is set to the maximum current trip level and nuisance tripping is occurring, select the next size MMP. (MS132-10 is the highest size in the MS132 frame size to meet Type E at 65kA; next size up is MS165-16.)
3. Requires use of the S1-M3-25 line side feeder terminal with the manual motor protector to meet Type E self-protection class.
4. 480Y/277 V delta systems only: Short-circuit protective devices with slash voltage ratings (e.g. 480Y/277 V) can be applied only in solidly grounded networks where the voltage from line-to-ground does not exceed the lower of the two ratings (e.g. 277 V AC), and the voltage from line-to-line does not exceed the higher of the two ratings (e.g. 480 V AC). The lower rating represents the device's interrupting capability per pole.
5. For all drives, the enclosure must be sized to accommodate the specific thermal considerations of the application as well as provide free space for cooling. For UL compliance the minimum enclosure volume is specified in the UL listing when applied with the ABB Type E MMP shown in the table. See the applicable ABB HW Manual for free space requirements.



# ACH, ACQ, ACS580 drives

## Purpose

This section outlines branch circuit protection that may be used with ACH, ACQ, ACS580-01, -04, -31, -34 drives through the R11 frame size.

## How to use this information

The drive hardware manual includes recommendations for suitable branch circuit protection for the drive. In addition to the protection identified in the manual, alternative branch circuit protection devices can be used. The guidelines in this document describe which branch circuit protective devices are acceptable alternatives. This document is a supplement to the following drive hardware manuals:

- 3AXD50000044839 ACH580-01 drives
- 3AXD50000044862 ACQ580-01 drives
- 3AXD50000044794 ACS580-01 drives
- 3AXD50000037066 ACH580-31 drives
- 3AXD50000045935 ACQ580-31 drives
- 3AXD50000048685 ACH580-04 drives
- 3AXD50000015497 ACS580-04 drives
- 3AXD50000048677 ACQ580-04 drives
- 3AXD500000419708 ACH580-34 drives
- 3AXD500000420025 ACQ580-34 drives

## Fuse Information

ACH580-01, ACQ580-01 and ACS580-01 drives are suitable for use on a circuit capable of delivering not more than 100 kA symmetrical amperes (RMS) at 240, 480 and 600 V maximum, when protected by appropriate fuses.

ACx580-04, -31 and -34 drives are suitable for use on a circuit capable of delivering not more than 100 kA symmetrical amperes (RMS) at 480 V maximum, when protected by appropriate fuses.

The drives are tested in accordance with standard UL 61800-5-1 on a circuit having available system fault current of 100 kA maximum.

Hardware manuals for ACx580-01, -04, -31, -34 drives provide required fusing guidelines :

- Listed Class CC (UL 248-4) fuses (up to 30A)
- Listed Class T (UL 248-15) fast acting fuses up to 600A
- Listed Class L (UL 248-15) fast acting fuses up to 1000A.

ABB performed the fault testing with “umbrella fuses.” These fuses are calibrated to create worst case peak let-through current ( $I_{peak}$ ) and let-through energy ( $I^2t$ ) in accordance with the limits of the intended fuse class(es) and ratings. The umbrella fuse testing allows other listed fuses, which have let-through characteristics equal to or below these limits, to be used. Therefore, listed (UL 248-8) Class J fast acting and high-speed fuses can also be used, since they provide equal or better protection. Likewise, listed (UL 248-17) fast acting cubed body (CF) fuses can be used as well.

**In addition to the above guidelines, the following additional rules must be followed. (These rules do not apply for ACx580-04 where semiconductor fuses can be used as alternate and ACx580-34 drives which use strictly semiconductor fuses):**

1. The UL listed fuses in the hardware manual tables, or the tables in this document, are the required branch circuit protection per NEC.
2. Fuses are required as part of the installation. Fuses are not included in the base drive configuration and must be provided by others.
3. Fuses with a higher current rating than specified must not be used.
4. Fuses with a lower current rating than specified may be used if they are of the same voltage and are UL 248 listed fast acting or high-speed fuses.
5. A fuse of a different class can be used at the high fault rating where the  $I_{peak}$  and  $I^2t$  of the new fuse is not greater than that of the specified fuse.
6. Recommended drive fuses must be used to maintain drive UL listing. Additional protection can be used. Refer to local codes and regulations.
7. When installing a drive always follow installation instructions and NEC requirements.
8. UL 248 listed, fast acting or high-speed fuses from other manufacturers can be used if they meet the rating requirements specified in the rules above.

Alternate recommended fuses for some of the major fuse manufacturers can be found in tables on the following pages. Other manufacturers not found on the tables below may be used if they meet the fuse requirements stated above.

**ACH, ACQ, ACS580-01, 208/230 V fuses**

Frame Size	208/230 V ACH580-01 ACQ580-01 ACS580-01	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-15 Class T Fast Acting Fuses				UL 248-8 Fast Acting Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R1	04A6-2	4.6	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	06A6-2	6.6	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	07A5-2	7.5	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	10A6-2	10.6	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	017A-2	16.7	30	600	JJS-30	JLLS030	A6T30	TJS30	JKS-30	JLS30	A4J30	JFL30
R2	024A-2	24.2	40	600	JJS-40	JLLS040	A6T40	TJS40	JKS-40	JLS40	A4J40	JFL40
R2	031A-2	30.8	40	600	JJS-40	JLLS040	A6T40	TJS40	JKS-40	JLS40	A4J40	JFL40
R3	046A-2	46.2	80	600	JJS-80	JLLS080	A6T80	TJS80	JKS-80	JLS80	A4J80	JFL80
R3	059A-2	59.4	80	600	JJS-80	JLLS080	A6T80	TJS80	JKS-80	JLS80	A4J80	JFL80
R4	075A-2	74.8	100	600	JJS-100	JLLS100	A6T100	TJS100	JKS-100	JLS100	A4J100	JFL100
R5	088A-2	88.0	150	600	JJS-150	JLLS150	A6T150	TJS150	JKS-150	JLS150	A4J150	JFL150
R5	114A-2	114	150	600	JJS-150	JLLS150	A6T150	TJS150	JKS-150	JLS150	A4J150	JFL150
R6	143A-2	143	200	600	JJS-200	JLLS200	A6T200	TJS200	JKS-200	JLS200	A4J200	JFL200
R7	169A-2	169	250	600	JJS-250	JLLS250	A6T250	TJS250	JKS-250	JLS250	A4T250	JFL250
R7	211A-2	211	300	600	JJS-300	JLLS300	A6T300	TJS300	JKS-300	JLS300	A4J300	JFL300
R8	273A-2	273	400	600	JJS-400	JLLS400	A6T400	TJS400	JKS-400	JLS400	A4J400	JFL400

Frame Size	208/230 V ACH580-01 ACQ580-01 ACS580-01	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 High Speed Class J Fuses				UL 248-4 Class CC Fast Acting Fuses				UL 248-17 Class CF Fast Acting Cube Fuse
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann
			A	V									
R1	04A6-2	4.6	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	06A6-2	6.6	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	07A5-2	7.5	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	10A6-2	10.6	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	017A-2	16.7	30	600	DFJ-30	LDFJ030	HSJ30	JHL30	KTK-R-30	KLKR30	ATMR30	HCLR30	FCF30RN
R2	024A-2	24.2	40	600	DFJ-40	LDFJ040	HSJ40	JHL40	-	-	-	-	FCF40RN
R2	031A-2	30.8	40	600	DFJ-40	LDFJ040	HSJ40	JHL40	-	-	-	-	FCF40RN
R3	046A-2	46.2	80	600	DFJ-80	LDFJ080	HSJ80	JHL80	-	-	-	-	FCF80RN
R3	059A-2	59.4	80	600	DFJ-80	LDFJ080	HSJ80	JHL80	-	-	-	-	FCF80RN
R4	075A-2	74.8	100	600	DFJ-100	LDFJ100	HSJ100	JHL100	-	-	-	-	FCF100RN
R5	088A-2	88.0	150	600	DFJ-150	LDFJ150	HSJ150	JHL150	-	-	-	-	-
R5	114A-2	114	150	600	DFJ-150	LDFJ150	HSJ150	JHL150	-	-	-	-	-
R6	143A-2	143	200	600	DFJ-200	LDFJ200	HSJ200	JHL200	-	-	-	-	-
R7	169A-2	169	250	600	DFJ-250	LDFJ250	HSJ250	JHL250	-	-	-	-	-
R7	211A-2	211	300	600	DFJ-300	LDFJ300	HSJ300	JHL300	-	-	-	-	-
R8	273A-2	273	400	600	DFJ-400	LDFJ400	HSJ400	JHL400	-	-	-	-	-

3AXD10001032874.xls Rev C

**ACH, ACQ, ACS580-01, 480 V fuses**

Frame Size	480 V ACH580-01- ACQ580-01- ACS580-01-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-15 Class T Fast Acting Fuses				UL 248-8 Fast Acting Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R1	02A1-4	2.1	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	03A0-4	3.0	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	03A5-4	3.5	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	04A8-4	4.8	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	07A6-4	7.6	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	012A-4	12.0	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R2	014A-4	14.0	30	600	JJS-30	JLLS030	A6T30	TJS30	JKS-30	JLS30	A4J30	JFL30
R2	023A-4	23.0	30	600	JJS-30	JLLS030	A6T30	TJS30	JKS-30	JLS30	A4J30	JFL30
R3	027A-4	27.0	40	600	JJS-40	JLLS040	A6T40	TJS40	JKS-40	JLS40	A4J40	JFL40
R3	034A-4	34.0	60	600	JJS-60	JLLS060	A6T60	TJS60	JKS-60	JLS60	A4J60	JFL60
R3	044A-4	44.0	60	600	JJS-60	JLLS060	A6T60	TJS60	JKS-60	JLS60	A4J60	JFL60
R4	052A-4	52	80	600	JJS-80	JLLS080	A6T80	TJS80	JKS-80	JLS80	A4J80	JFL80
R4	065A-4	65	100	600	JJS-100	JLLS100	A6T100	TJS100	JKS-100	JLS100	A4J100	JFL100
R4	077A-4	77	100	600	JJS-100	JLLS100	A6T100	TJS100	JKS-100	JLS100	A4T100	JFL100
R5	096A-4	96	150	600	JJS-150	JLLS150	A6T150	TJS150	JKS-150	JLS150	A4J150	JFL150
R6	124A-4	124	200	600	JJS-200	JLLS200	A6T200	TJS200	JKS-200	JLS200	A4J200	JFL200
R7	156A-4	156	225	600	JJS-225	JLLS225	A6T225	TJS225	JKS-225	JLS225	A4J225	JFL225
R7	180A-4	180	300	600	JJS-300	JLLS300	A6T300	TJS300	JKS-300	JLS300	A4J300	JFL300
R8	240A-4	240	350	600	JJS-350	JLLS350	A6T350	TJS350	JKS-350	JLS350	A4J350	JFL350
R8*	260A-4	240	400	600	JJS-400	JLLS400	A6T400	TJS400	JKS-400	JLS400	A4J400	JFL400
R9	302A-4	302	500	600	JJS-500	JLLS500	A6T500	TJS500	UL Approval Pending			
R9	361A-4	361	500	600	JJS-500	JLLS500	A6T500	TJS500				
R9	414A-4	414	600	600	JJS-600	JLLS600	A6T600	TJS600				

Frame Size	480 V ACH580-01- ACQ580-01- ACS580-01-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 High Speed Class J Fuses				UL 248-4 Class CC Fast Acting Fuses				UL 248-17 Class CF Fast Acting Cube Fuse
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann
			A	V									
R1	02A1-4	2.1	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	03A0-4	3.0	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	03A5-4	3.5	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	04A8-4	4.8	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	07A6-4	7.6	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	012A-4	12.0	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R2	014A-4	14.0	30	600	DFJ-30	LDFJ030	HSJ30	JHL30	KTK-R-30	KLKR30	ATMR30	HCLR30	FCF30RN
R2	023A-4	23.0	30	600	DFJ-30	LDFJ030	HSJ30	JHL30	KTK-R-30	KLKR30	ATMR30	HCLR30	FCF30RN
R3	027A-4	27.0	40	600	DFJ-40	LDFJ040	HSJ40	JHL40	-	-	-	-	FCF40RN
R3	034A-4	34.0	60	600	DFJ-60	LDFJ060	HSJ60	JHL60	-	-	-	-	FCF60RN
R3	044A-4	44.0	60	600	DFJ-60	LDFJ060	HSJ60	JHL60	-	-	-	-	FCF60RN
R4	052A-4	52	80	600	DFJ-80	LDFJ080	HSJ80	JHL80	-	-	-	-	FCF80RN
R4	065A-4	65	100	600	DFJ-100	LDFJ100	HSJ100	JHL100	-	-	-	-	FCF100RN
R4	077A-4	77	100	600	DFJ-100	LDFJ100	HSJ100	JHL100	-	-	-	-	-
R5	096A-4	96	150	600	DFJ-150	LDFJ150	HSJ150	JHL150	-	-	-	-	-
R6	124A-4	124	200	600	DFJ-200	LDFJ200	HSJ200	JHL200	-	-	-	-	-
R7	156A-4	156	225	600	DFJ-225	LDFJ225	HSJ225	JHL225	-	-	-	-	-
R7	180A-4	180	300	600	DFJ-300	LDFJ300	HSJ300	JHL300	-	-	-	-	-
R8	240A-4	240	350	600	DFJ-350	LDFJ350	HSJ350	JHL350	-	-	-	-	-
R8*	260A-4	240	400	600	DFJ-400	LDFJ400	HSJ400	JHL400	-	-	-	-	-
R9	302A-4	302	500	600	UL Approval Pending				-	-	-	-	-
R9	361A-4	361	500	600					-	-	-	-	-
R9	414A-4	414	600	600					-	-	-	-	-

\*Not available in ACH580

**ACH, ACQ, ACS580-01, 575 V fuses**

Frame Size	575 V ACH580-01- ACQ580-01- ACS580-01-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-15 Class T Fast Acting Fuses				UL 248-8 Fast Acting Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R2	02A7-6	2.7	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R2	03A9-6	3.9	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R2	06A1-6	6.1	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R2	09A0-6	9	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R2	011A-6	11	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R2	017A-6	17	30	600	JJS-30	JLLS030	A6T30	TJS30	JKS-30	JLS30	A4J30	JFL30
R3	022A-6	22	40	600	JJS-40	JLLS040	A6T40	TJS40	JKS-40	JLS40	A4J40	JFL40
R3	027A-6	27	40	600	JJS-40	JLLS040	A6T40	TJS40	JKS-40	JLS40	A4J40	JFL40
R3	032A-6	32	40	600	JJS-40	JLLS040	A6T40	TJS40	JKS-40	JLS40	A4J40	JFL40
R5	041A-6	41	100	600	JJS-100	JLLS100	A6T100	TJS100	JKS-100	JLS100	A4T100	JFL100
R5	052A-6	52	100	600	JJS-100	JLLS100	A6T100	TJS100	JKS-100	JLS100	A4T100	JFL100
R5	062A-6	62	100	600	JJS-100	JLLS100	A6T100	TJS100	JKS-100	JLS100	A4T100	JFL100
R5	077A-6	77	100	600	JJS-100	JLLS100	A6T100	TJS100	JKS-100	JLS100	A4T100	JFL100
R7	099A-6	99	150	600	JJS-150	JLLS150	A6T150	TJS150	JKS-150	JLS150	A4J150	JFL150
R7	125A-6	125	200	600	JJS-200	JLLS200	A6T200	TJS200	JKS-200	JLS200	A4J200	JFL200
R8	144A-6	144	250	600	JJS-250	JLLS250	A6T250	TJS250	JKS-250	JLS250	A4J250	JFL250
R9	192A-6	192	300	600	JJS-300	JLLS300	A6T300	TJS300	UL Approval Pending			
R9	242A-6	242	400	600	JJS-400	JLLS400	A6T400	TJS400				
R9	271A-6	271	400	600	JJS-400	JLLS400	A6T400	TJS400				

Frame Size	575 V ACH580-01- ACQ580-01- ACS580-01-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 High Speed Class J Fuses				UL 248-4 Class CC Fast Acting Fuses				UL 248-17 Class CF Fast Acting Cube Fuse
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann
			A	V									
R2	02A7-6	2.7	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R2	03A9-6	3.9	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R2	06A1-6	6.1	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R2	09A0-6	9	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R2	011A-6	11	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R2	017A-6	17	30	600	DFJ-30	LDFJ030	HSJ30	JHL30	KTK-R-30	KLKR30	ATMR30	HCLR30	FCF30RN
R3	022A-6	22	40	600	DFJ-40	LDFJ040	HSJ40	JHL40	-	-	-	-	FCF40RN
R3	027A-6	27	40	600	DFJ-40	LDFJ040	HSJ40	JHL40	-	-	-	-	FCF40RN
R3	032A-6	32	40	600	DFJ-40	LDFJ040	HSJ40	JHL40	-	-	-	-	FCF40RN
R5	041A-6	41	100	600	DFJ-100	LDFJ100	HSJ100	JHL100	-	-	-	-	FCF100RN
R5	052A-6	52	100	600	DFJ-100	LDFJ100	HSJ100	JHL100	-	-	-	-	FCF100RN
R5	062A-6	62	100	600	DFJ-100	LDFJ100	HSJ100	JHL100	-	-	-	-	FCF100RN
R5	077A-6	77	100	600	DFJ-100	LDFJ100	HSJ100	JHL100	-	-	-	-	FCF100RN
R7	099A-6	99	150	600	DFJ-150	LDFJ150	HSJ150	JHL150	-	-	-	-	-
R7	125A-6	125	200	600	DFJ-200	LDFJ200	HSJ200	JHL200	-	-	-	-	-
R8	144A-6	144	250	600	DFJ-250	LDFJ250	HSJ250	JHL250	-	-	-	-	-
R9	192A-6	192	300	600	UL Approval Pending				-	-	-	-	-
R9	242A-6	242	400	600					-	-	-	-	-
R9	271A-6	271	400	600					-	-	-	-	-

3AXD10001032874.xls Rev C

**ACH, ACQ580-04, 480 V fuses**

Frame Size	480 V ACH580-04- ACQ580-04-	Input Current	UL Fuse Size (A) and Voltage (V)		UL248-15 Class T Fast Acting Fuses				UL 248-10 Fast Acting Class L Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R10	505A-4	505	600	600	JJS-600	JLLS600	A6T600	TJS600	-	-	-	-
R10	585A-4	585	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
R10	650A-4	650	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
R11	725A-4	725	1000	600	-	JLLS1000	-	-	KTU-1000	LDC1000	A4BY1000	LCU1000
R11	820A-4	820	1000	600	-	JLLS1000	-	-	KTU-1000	LDC1000	A4BY1000	LCU1000
R11	880A-4	880	1000	600	-	JLLS1000	-	-	KTU-1000	LDC1000	A4BY1000	LCU1000

Frame Size	480 V ACH580-04- ACQ580-04-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 Fast Acting Class J Fuses				UL 248-8 High Speed Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R10	505A-4	505	600	600	JKS-600	JLS600	A4J600	JFL600	DFJ-600	LDFJ600	HSJ600	JHL600
R10	585A-4	585	800	600	-	-	-	-	-	-	-	-
R10	650A-4	650	800	600	-	-	-	-	-	-	-	-
R11	725A-4	725	1000	600	-	-	-	-	-	-	-	-
R11	820A-4	820	1000	600	-	-	-	-	-	-	-	-
R11	880A-4	880	1000	600	-	-	-	-	-	-	-	-

Frame Size	480 V ACH580-04- ACQ580-04-	Input Current	UL Fuse Size (A) and Voltage (V)		Bussmann Semiconductor Fuses UL 248-13 Recognized Fuses				
			Maximum Current	Voltage Rating	Type Flush End	Type DIN 43463	Type US Style	Type French Style	Type DIN 43620
			A	V					
R10	505A-4	505	700	690	170M6411	170M6011	170M6611	170M6311	170M6811D
R10	585A-4	585	700	690	170M6411	170M6011	170M6611	170M6311	170M6811D
R10	650A-4	650	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D
R11	725A-4	725	900	690	170M6413	170M6013	170M6613	170M6313	170M6813D
R11	820A-4	820	1000	690	170M6414	170M6014	170M6614	170M6314	170M6814D
R11	880A-4	880	1400	690	170M6417	170M6017	170M6617	170M6317	170M8555D

3AXD10001032874.xls Rev C

**ACH, ACQ580-31, 480 V fuses**

Frame Size	480 V ACH580-31- ACQ580-31-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-15 Class T Fast Acting Fuses				UL 248-8 Fast Acting Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R3	07A6-4	7	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R3	012A-4	9	20	600	JJS-20	JLLS020	A6T20	TJS20	JKS-20	JLS20	A4J20	JFL20
R3	014A-4	12	25	600	JJS-25	JLLS025	A6T25	TJS25	JKS-25	JLS25	A4J25	JFL25
R3	023A-4	17	35	600	JJS-35	JLLS035	A6T35	TJS35	JKS-35	JLS35	A4J35	JFL35
R6	027A-4	24	40	600	JJS-40	JLLS040	A6T40	TJS40	JKS-40	JLS40	A4J40	JFL40
R6	034A-4	29	50	600	JJS-50	JLLS050	A6T50	TJS50	JKS-50	JLS50	A4J50	JFL50
R6	044A-4	34	60	600	JJS-60	JLLS060	A6T60	TJS60	JKS-60	JLS60	A4J60	JFL60
R6	052A-4	44	80	600	JJS-80	JLLS080	A6T80	TJS80	JKS-80	JLS80	A4J80	JFL80
R6	065A-4	54	90	600	JJS-90	JLLS090	A6T90	TJS90	JKS-90	JLS90	A4J90	JFL90
R6	077A-4	66	110	600	JJS-110	JLLS110	A6T110	TJS110	JKS-110	JLS110	A4J110	JFL110
R8	096A-4	82	150	600	JJS-150	JLLS150	A6T150	TJS150	JKS-150	JLS150	A4J150	JFL150
R8	124A-4	111	200	600	JJS-200	JLLS200	A6T200	TJS200	JKS-200	JLS200	A4J200	JFL200
R8	156A-4	134	225	600	JJS-225	JLLS225	A6T225	TJS225	JKS-225	JLS225	A4J225	JFL225
R8	180A-4	163	300	600	JJS-300	JLLS300	A6T300	TJS300	JKS-300	JLS300	A4T300	JFL300

Frame Size	480 V ACH580-31- ACQ580-31-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 High Speed Class J Fuses				UL 248-4 Class CC Fast Acting Fuses				UL 248-17 Class CF Fast Acting Cube Fuse
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann
			A	V									
R3	07A6-4	7	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R3	012A-4	9	20	600	DFJ-20	LDFJ020	HSJ20	JHL20	KTK-R-20	KLKR20	ATMR20	HCLR20	FCF20RN
R3	014A-4	12	25	600	DFJ-25	LDFJ025	HSJ25	JHL25	KTK-R-25	KLKR25	ATMR25	HCLR25	FCF25RN
R3	023A-4	17	35	600	DFJ-35	LDFJ035	HSJ35	JHL35	-	-	-	-	FCF35RN
R6	027A-4	24	40	600	DFJ-40	LDFJ040	HSJ40	JHL40	-	-	-	-	FCF40RN
R6	034A-4	29	50	600	DFJ-50	LDFJ050	HSJ50	JHL50	-	-	-	-	FCF50RN
R6	044A-4	34	60	600	DFJ-60	LDFJ060	HSJ60	JHL60	-	-	-	-	FCF60RN
R6	052A-4	44	80	600	DFJ-80	LDFJ080	HSJ80	JHL80	-	-	-	-	FCF80RN
R6	065A-4	54	90	600	DFJ-90	LDFJ090	HSJ90	JHL90	-	-	-	-	FCF90RN
R6	077A-4	66	110	600	DFJ-110	LDFJ110	HSJ110	JHL110	-	-	-	-	-
R8	096A-4	82	150	600	DFJ-150	LDFJ150	HSJ150	JHL150	-	-	-	-	-
R8	124A-4	111	200	600	DFJ-200	LDFJ200	HSJ200	JHL200	-	-	-	-	-
R8	156A-4	134	225	600	DFJ-225	LDFJ225	HSJ225	JHL225	-	-	-	-	-
R8	180A-4	163	300	600	DFJ-300	LDFJ300	HSJ300	JHL300	-	-	-	-	-

3AXD10001032874.xls Rev C

**ACH, ACQ580-34, 480 V fuses**

Frame Size	480 V ACH580-34- ACQ580-34-	Input Current	UL Fuse Size (A) and Voltage (V)		Bussmann Semiconductor Fuses UL 248-13 Recognized Fuses			
			Maximum Current	Voltage Rating	Type Flush End	Type DIN 43463	Type US Style	Type French Style
			A	V				
R11	240A-4	209	400	690	170M5408	170M5008	170M5608	170M5308
R11	302A-4	258	500	690	170M5410	170M5010	170M5610	170M5310
R11	361A-4	307	630	690	170M6410	170M6010	170M6610	170M6310
R11	414A-4	363	700	690	170M6411	170M6011	170M6611	170M6311
R11	477A-4	414	800	690	170M6412	170M6012	170M6612	170M6312

3AXD10001032874.xls Rev C

### **Circuit Breaker Information**

ACx580-01 drives are suitable for use on a circuit capable of delivering not more than 65 kA symmetrical amperes (RMS) at 240 / 480 V maximum, when protected by appropriate circuit breakers in the tables below. Depending upon the voltage use either the rules in the 240V paragraph just below, or the 480V paragraph just below that, and then also use rules 1-4 below those.

**ACx580-01 230V** drives were tested with ABB inverse time circuit breakers rated at 65kA and 240V. When using circuit breakers to protect these drives follow these initial rules:

- Other manufacturers' inverse time circuit breakers can be used if they are UL 489 listed, they are 240V or higher, they have a 65kA or higher interrupting capacity and they have the same or lower nominal current rating than ABB specified circuit breaker.
- Current limiting inverse time circuit breakers must not be used.

**ACx580-01 460V** drives were tested with ABB current limiting inverse time circuit breakers rated at 65kA and 480V. When using circuit breakers to protect these drives follow these initial rules:

- When designing UL508A panels, Article SB 4.2.3 Exception No. 3 allows the use of other manufacturers' current limiting inverse time circuit breakers which have same voltage, current and interrupting rating, if  $I_{peak}$  and  $I^2t$  are the same or less than the ABB specified circuit breaker.
- Non-current limiting inverse time circuit breakers must not be used.
- Enclosures for frames R1, R3, and R9 must have a solid bottom directly below the drive. i.e. fans, filters or louvers cannot be mounted directly below the drive but can be mounted in adjacent areas on the bottom of the enclosure.

### **Follow these additional rules for all voltages.**

1. Drive must be mounted in an enclosure  $\geq$  Enclosure Minimum Volume listed in the table below.
2. When multiple drives are installed in the same enclosure, minimum volume of the enclosure is determined by largest Enclosure Minimum Volume of the drives to be placed in the enclosure, plus the volume(s) of each additional drive. i.e. for the 480V R6 and R3 drive select enclosure with the volume  $\geq 53703+991 = 54694 \text{ in}^3$ .
3. Open Type, Type 1 and Type 12 drives can be used inside of the enclosure. Use drive volume for all three types listed in the table when installing multiple drives in the panel.
4. The ABB circuit breaker part number listed in the table is a base part number. The last eight characters of the breaker "FF000XXX" represent optional accessories which can be added to the breaker. These accessories have no impact on the performance or rating of the breakers.



**ACH, ACQ, ACS580-01, 230 V circuit breakers**

Frame Size	230 V ACH580-01- ACQ580-01- ACS580-01-	Input Current (A)	CB Nominal Current (A)	CB Voltage (V)	Enclosure Minimum Volume (in <sup>3</sup> )	Drive Volume (in <sup>3</sup> )	Circuit Breaker (ABB) 65kA @ 240 V	
R1	04A6-2	4.6	25	240	6480	376	XT2NU3025AFF000XXX	
R1	06A6-2	6.6	25	240	6480	376	XT2NU3025AFF000XXX	
R1	07A5-2	7.5	25	240	6480	376	XT2NU3025AFF000XXX	
R1	10A6-2	10.6	25	240	6480	376	XT2NU3025AFF000XXX	
R1	017A-2	16.7	25	240	6480	376	XT2NU3025AFF000XXX	
R2	024A-2	24.2	40	240	6480	376	XT2NU3040AFF000XXX	
R2	031A-2	30.8	40	240	6480	532	XT2NU3040AFF000XXX	
R3	046A-2	46.2	100	240	6480	532	XT2NU3100BFF000XXX	
R3	059A-2	59.4	100	240	6480	991	XT2NU3100BFF000XXX	
R4	075A-2	74.8	100	240	6480	991	XT2NU3100BFF000XXX	
R5	088A-2	88.0	UL Approval Pending					
R5	114A-2	114						
R6	143A-2	143						
R7	169A-2	169						
R7	211A-2	211						
R8	273A-2	273						

**ACH, ACQ, ACS580-01, 480 V circuit breakers**

Frame Size	480 V ACH580-01- ACQ580-01- ACS580-01-	Input Current (A)	CB Nominal Current (A)	CB Voltage (V)	Enclosure Minimum Volume (in <sup>3</sup> )	Drive Volume (in <sup>3</sup> )	Circuit Breaker (ABB) 65kA @ 480V	Circuit Breaker (Rockwell) 65kA @ 480 V	Maximum I <sup>2</sup> t (A <sup>2</sup> s)	Maximum I <sub>peak</sub> (kA)	
R1	02A1-4	2.1	20	480	6480	376	XT2HU3020AFF000XXX	140G-HC6C3-C20	0.512x10 <sup>6</sup>	23.2	
R1	03A0-4	3.0	20	480	6480	376	XT2HU3020AFF000XXX	140G-HC6C3-C20	0.512x10 <sup>6</sup>	23.2	
R1	03A5-4	3.5	20	480	6480	376	XT2HU3020AFF000XXX	140G-HC6C3-C20	0.512x10 <sup>6</sup>	23.2	
R1	04A8-4	4.8	20	480	6480	376	XT2HU3020AFF000XXX	140G-HC6C3-C20	0.512x10 <sup>6</sup>	23.2	
R1	07A6-4	7.6	20	480	6480	376	XT2HU3020AFF000XXX	140G-HC6C3-C20	0.512x10 <sup>6</sup>	23.2	
R1	012A-4	12.0	20	480	6480	376	XT2HU3020AFF000XXX	140G-HC6C3-C20	0.512x10 <sup>6</sup>	23.2	
R2	014A-4	14.0	35	480	16200	532	XT2HU3035AFF000XXX	140G-HC6C3-C35	0.512x10 <sup>6</sup>	23.2	
R2	023A-4	23.0	35	480	16200	532	XT2HU3035AFF000XXX	140G-HC6C3-C35	0.512x10 <sup>6</sup>	23.2	
R3	027A-4	27.0	70	480	27720	991	XT2HU3070AFF000XXX	140G-HC6C3-C70	0.512x10 <sup>6</sup>	23.2	
R3	034A-4	34.0	70	480	27720	991	XT2HU3070AFF000XXX	140G-HC6C3-C70	0.512x10 <sup>6</sup>	23.2	
R3	044A-4	44.0	70	480	27720	991	XT2HU3070AFF000XXX	140G-HC6C3-C70	0.512x10 <sup>6</sup>	23.2	
R4	052A-4	52	125	480	30240	1404	XT2HU3125AFF000XXX	140G-HC6H3-D12	0.512x10 <sup>6</sup>	23.2	
R4	065A-4	65	125	480	30240	1404	XT2HU3125AFF000XXX	140G-HC6H3-D12	0.512x10 <sup>6</sup>	23.2	
R4	077A-4	77	125	480	30240	1404	XT2HU3125EFF000XXX	140G-HC6H3-D12	0.512x10 <sup>6</sup>	23.2	
R5	096A-4	96	150	480	30240	1805	XT4HU3150EFF000XXX	140G-HC6H3-D15	0.98x10 <sup>6</sup>	30	
R6	124A-4	124	225	480	53703	2365	XT4HU3225EFF000XXX	140G-JC6H3-D25	0.98x10 <sup>6</sup>	30	
R7	156A-4	156	250	480	53703	2948	XT4HU3250EFF000XXX	140G-JC6H3-D25	0.98x10 <sup>6</sup>	30	
R7	180A-4	180	250	480	53703	2948	XT4HU3250EFF000XXX	140G-JC6H3-D25	0.98x10 <sup>6</sup>	30	
R8	240A-4	240	400	480	53703	3858	XT5HU340AEFF000XXX	140G-KC6H3-D40	4.2x10 <sup>6</sup>	47.9	
R8	260A-4	240	400	480	53703	3858	XT5HU340AEFF000XXX	140G-KC6H3-D40	4.2x10 <sup>6</sup>	47.9	
R9	302A-4	302	UL Approval Pending								
R9	361A-4	361									
R9	414A-4	414									

3AXD10001032874.xls Rev C

# ACS880 drives

## Purpose

This section outlines branch circuit protection that may be used with ACS880-01, -04, 04XT, -04F, 04FXT, -11, -14, -31, -34 drives.

## How to use this information

The drive hardware manual includes branch circuit protection recommendations for the drive. In addition to the branch circuit protection identified in the manual, alternative devices can be used if they meet certain characteristics. The guidelines in this document describe which fuses and circuit breakers are an acceptable alternative. This document is a supplement to the following drive hardware manuals:

- 3AUA0000078093 ACS880-01 drives
- 3AUA0000128301 ACS880-04 drives
- 3AXD500000025169 ACS880-04XT drives
- 3AXD500000034664 ACS880-04F drives
- 3AXD50000274444 ACS880-04FXT drives
- 3AXD50000045932 ACS880-11 drives
- 3AXD50000035160 ACS880-14 drives
- 3AXD50000045933 ACS880-31 drives
- 3AXD50000035191 ACS880-34 drives

## Fuse Information

ACS880-01 drives are suitable for use on a circuit capable of delivering not more than 100 kA symmetrical amperes (RMS) at 240, 480 and 600 V maximum, when protected by appropriate fuses.

ACS880-11 and -31 drives are suitable for use on a circuit capable of delivering not more than 100 kA symmetrical amperes (RMS) at 480 V maximum when protected by appropriate fuses.

ACS880-04, -04F, -04XT, -04FXT, -14 and -34 drives are suitable for use on a circuit capable of delivering not more than 100 kA symmetrical amperes (RMS) at 480 and 600 V maximum when protected by appropriate fuses.

The drives are tested in accordance with standard UL 61800-5-1 on a circuit having available system fault current of 100 kA maximum.

Hardware manuals for ACS880-01, -04, -11, -14, -31, and -34 drives provided fusing guidelines:

- Listed Class CC (UL 248-4) fuses (up to 30A)
- Listed Class T (UL 248-15) fast acting fuses up to 600A
- Listed Class L (UL 248-15) fast acting fuses up to 1000A.

ABB performed the fault testing with “umbrella fuses.” These fuses are calibrated to create worst case peak let-through current ( $I_{peak}$ ) and let-through energy ( $I^2t$ ) in accordance with the limits of the intended fuse class(es) and ratings. The umbrella fuse testing allows other Listed fuses, which have let-through characteristics equal to or below these limits, to be used. Therefore, listed (UL 248-8) Class J fast acting and

high-speed fuses can also be used, since they provide equal or better protection. Likewise, listed (UL 248-17) fast acting cubed body (CF) fuses can be used as well.

**In addition to the above guidelines, the following rules must be followed. (These rules do not apply for the ACS880-04 drives where semiconductor fuses can be used as alternate and ACS880-14 and -34 drives which use strictly semiconductor fuses):**

1. The UL listed fuses in the hardware manual tables, or the tables in this document, are the required branch circuit protection per NEC.
2. Fuses are required as part of the installation. Fuses are not included in the base drive configuration and must be provided by others.
3. Fuses with a higher current rating than specified must not be used.
4. Fuses with a lower current rating than specified may be used if they are of the same voltage and are UL 248 listed fast acting or high-speed fuses.
5. A fuse of a different class can be used at the high fault rating where the  $I_{peak}$  and  $I^2t$  of the new fuse is not greater than that of the specified fuse.
6. Recommended drive fuses must be used to maintain drive UL listing. Additional protection can be used. Refer to local codes and regulations.
7. When installing a drive always follow installation instructions and NEC requirements.
8. UL 248 listed, fast acting or high-speed fuses from other manufacturers can be used if they meet the rating requirements specified in the rules above.

Alternate recommended fuses for some of the major fuse manufacturers can be found in tables on the following pages. Other manufacturers not found on the tables below may be used if they meet the fuse requirements stated above.

**ACS880-01, 230 V fuses**

Frame Size	230 V ACS880-01-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-15 Class T Fast Acting Fuses				UL 248-8 Fast Acting Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison
			A	V								
R1	04A6-2	4.4	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	06A6-2	6.3	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	07A5-2	7.1	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	10A6-2	10.1	20	600	JJS-20	JLLS020	A6T20	TJS20	JKS-20	JLS20	A4J20	JFL20
R2	16A8-2	16.0	25	600	JJS-25	JLLS025	A6T25	TJS25	JKS-25	JLS25	A4J25	JFL25
R2	24A3-2	23.1	35	600	JJS-35	JLLS035	A6T35	TJS35	JKS-35	JLS35	A4J35	JFL35
R3	031A-2	29.3	50	600	JJS-50	JLLS050	A6T50	TJS50	JKS-50	JLS50	A4J50	JFL50
R4	046A-2	44.0	80	600	JJS-80	JLLS080	A6T80	TJS80	JKS-80	JLS80	A4J80	JFL80
R4	061A-2	58.0	80	600	JJS-80	JLLS080	A6T80	TJS80	JKS-80	JLS80	A4J80	JFL80
R5	075A-2	71.0	110	600	JJS-110	JLLS110	A6T110	TJS110	JKS-110	JLS110	A4J110	JFL110
R5	087A-2	83.0	110	600	JJS-110	JLLS110	A6T110	TJS110	JKS-110	JLS110	A4J110	JFL110
R6	115A-2	109	150	600	JJS-150	JLLS150	A6T150	TJS150	JKS-150	JLS150	A4J150	JFL150
R6	145A-2	138	200	600	JJS-200	JLLS200	A6T200	TJS200	JKS-200	JLS200	A4J200	JFL200
R7	170A-2	162	250	600	JJS-250	JLLS250	A6T250	TJS250	JKS-250	JLS250	A4T250	JFL250
R7	206A-2	196	300	600	JJS-300	JLLS300	A6T300	TJS300	JKS-300	JLS300	A4J300	JFL300
R8	274A-2	260	400	600	JJS-400	JLLS400	A6T400	TJS400	JKS-400	JLS400	A4J400	JFL400

Frame Size	230 V ACS880-01-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 High Speed Class J Fuses				UL 248-4 Class CC Fast Acting Fuses				UL 248-17 Class CF Fast Acting Cube Fuse
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison	Bussmann
			A	V									
R1	04A6-2	4.4	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	06A6-2	6.3	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	07A5-2	7.1	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	10A6-2	10.1	20	600	DFJ-20	LDFJ020	HSJ20	JHL20	KTK-R-20	KLKR20	ATMR20	HCLR20	FCF20RN
R2	16A8-2	16.0	25	600	DFJ-25	LDFJ025	HSJ25	JHL25	KTK-R-25	KLKR25	ATMR25	HCLR25	FCF25RN
R2	24A3-2	23.1	35	600	DFJ-35	LDFJ035	HSJ35	JHL35	-	-	-	-	FCF35RN
R3	031A-2	29.3	50	600	DFJ-50	LDFJ050	HSJ50	JHL50	-	-	-	-	FCF50RN
R4	046A-2	44.0	80	600	DFJ-80	LDFJ080	HSJ80	JHL80	-	-	-	-	FCF80RN
R4	061A-2	58.0	80	600	DFJ-80	LDFJ080	HSJ80	JHL80	-	-	-	-	FCF80RN
R5	075A-2	71.0	110	600	DFJ-110	LDFJ110	HSJ110	JHL110	-	-	-	-	-
R5	087A-2	83.0	110	600	DFJ-110	LDFJ110	HSJ110	JHL110	-	-	-	-	-
R6	115A-2	109	150	600	DFJ-150	LDFJ150	HSJ150	JHL150	-	-	-	-	-
R6	145A-2	138	200	600	DFJ-200	LDFJ200	HSJ200	JHL200	-	-	-	-	-
R7	170A-2	162	250	600	DFJ-250	LDFJ250	HSJ250	JHL250	-	-	-	-	-
R7	206A-2	196	300	600	DFJ-300	LDFJ300	HSJ300	JHL300	-	-	-	-	-
R8	274A-2	260	400	600	DFJ-400	LDFJ400	HSJ400	JHL400	-	-	-	-	-

3AXD10001032874.xls Rev C

**ACS880-01, 480 V fuses**

Frame Size	480 V ACS880-01-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-15 Class T Fast Acting Fuses				UL 248-8 Fast Acting Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison
			A	V								
R1	02A1-5	2.1	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	03A0-5	3.0	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	03A4-5	3.4	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	04A8-5	4.8	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	05A2-5	5.2	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	07A6-5	7.6	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R1	11A0-5	11	20	600	JJS-20	JLLS020	A6T20	TJS20	JKS-20	JLS20	A4J20	JFL20
R2	014A-5	14	25	600	JJS-25	JLLS025	A6T25	TJS25	JKS-25	JLS25	A4J25	JFL25
R2	021A-5	21	35	600	JJS-35	JLLS035	A6T35	TJS35	JKS-35	JLS35	A4J35	JFL35
R3	027A-5	27	40	600	JJS-40	JLLS040	A6T40	TJS40	JKS-40	JLS40	A4J40	JFL40
R3	034A-5	34	50	600	JJS-50	JLLS050	A6T50	TJS50	JKS-50	JLS50	A4J50	JFL50
R4	040A-5	40	60	600	JJS-60	JLLS060	A6T60	TJS60	JKS-60	JLS60	A4J60	JFL60
R4	052A-5	52	80	600	JJS-80	JLLS080	A6T80	TJS80	JKS-80	JLS80	A4J80	JFL80
R5	065A-5	65	90	600	JJS-90	JLLS090	A6T90	TJS90	JKS-90	JLS90	A4J90	JFL90
R5	077A-5	77	110	600	JJS-110	JLLS110	A6T110	TJS110	JKS-110	JLS110	A4J110	JFL110
R6	096A-5	96	150	600	JJS-150	JLLS150	A6T150	TJS150	JKS-150	JLS150	A4J150	JFL150
R6	124A-5	124	200	600	JJS-200	JLLS200	A6T200	TJS200	JKS-200	JLS200	A4J200	JFL200
R7	156A-5	156	225	600	JJS-225	JLLS225	A6T225	TJS225	JKS-225	JLS225	A4J225	JFL225
R7	180A-5	180	300	600	JJS-300	JLLS300	A6T300	TJS300	JKS-300	JLS300	A4J300	JFL300
R8	240A-5	240	350	600	JJS-350	JLLS350	A6T350	TJS350	JKS-350	JLS350	A4J350	JFL350
R8	260A-5	260	400	600	JJS-400	JLLS400	A6T400	TJS400	JKS-400	JLS400	A4J400	JFL400
R9	302A-5	302	400	600	JJS-400	JLLS400	A6T400	TJS400	UL Approval Pending			
R9	361A-5	361	500	600	JJS-500	JLLS500	A6T500	TJS500				
R9	414A-5	414	600	600	JJS-600	JLLS600	A6T600	TJS600				

Frame Size	480 V ACS880-01	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 High Speed Class J Fuses				UL 248-4 Class CC Fast Acting Fuses				UL 248-17 Class CF Fast Acting Cube Fuse
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison	Bussmann
			A	V									
R1	02A1-5	2.1	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	03A0-5	3.0	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	03A4-5	3.4	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	04A8-5	4.8	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	05A2-5	5.2	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	07A6-5	7.6	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R1	11A0-5	11	20	600	DFJ-20	LDFJ020	HSJ20	JHL20	KTK-R-20	KLKR20	ATMR20	HCLR20	FCF20RN
R2	014A-5	14	25	600	DFJ-25	LDFJ025	HSJ25	JHL25	KTK-R-25	KLKR25	ATMR25	HCLR25	FCF25RN
R2	021A-5	21	35	600	DFJ-35	LDFJ035	HSJ35	JHL35	-	-	-	-	FCF35RN
R3	027A-5	27	40	600	DFJ-40	LDFJ040	HSJ40	JHL40	-	-	-	-	FCF40RN
R3	034A-5	34	50	600	DFJ-50	LDFJ050	HSJ50	JHL50	-	-	-	-	FCF50RN
R4	040A-5	40	60	600	DFJ-60	LDFJ060	HSJ60	JHL60	-	-	-	-	FCF60RN
R4	052A-5	52	80	600	DFJ-80	LDFJ080	HSJ80	JHL80	-	-	-	-	FCF80RN
R5	065A-5	65	90	600	DFJ-90	LDFJ090	HSJ90	JHL90	-	-	-	-	FCF90RN
R5	077A-5	77	110	600	DFJ-110	LDFJ110	HSJ110	JHL110	-	-	-	-	-
R6	096A-5	96	150	600	DFJ-150	LDFJ150	HSJ150	JHL150	-	-	-	-	-
R6	124A-5	124	200	600	DFJ-200	LDFJ200	HSJ200	JHL200	-	-	-	-	-
R7	156A-5	156	225	600	DFJ-225	LDFJ225	HSJ225	JHL225	-	-	-	-	-
R7	180A-5	180	300	600	DFJ-300	LDFJ300	HSJ300	JHL300	-	-	-	-	-
R8	240A-5	240	350	600	DFJ-350	LDFJ350	HSJ350	JHL350	-	-	-	-	-
R8	260A-5	260	400	600	DFJ-400	LDFJ400	HSJ400	JHL400	-	-	-	-	-
R9	302A-5	302	400	600	UL Approval Pending				-	-	-	-	-
R9	361A-5	361	500	600					-	-	-	-	
R9	414A-5	414	600	600					-	-	-	-	

3AXD10001032874.xls Rev C

**ACS880-01, 575 V fuses**

Frame Size	575 V ACS880-01-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-15 Class T Fast Acting Fuses				UL 248-8 Fast Acting Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R3	07A4-7	7	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R3	09A9-7	9.4	20	600	JJS-20	JLLS020	A6T20	TJS20	JKS-20	JLS20	A4J20	JFL20
R3	14A3-7	13.6	30	600	JJS-30	JLLS030	A6T30	TJS30	JKS-30	JLS30	A4J30	JFL30
R3	019A-7	18	40	600	JJS-40	JLLS040	A6T40	TJS40	JKS-40	JLS40	A4J40	JFL40
R3	023A-7	22	50	600	JJS-50	JLLS050	A6T50	TJS50	JKS-50	JLS50	A4J50	JFL50
R3	027A-7	27	50	600	JJS-50	JLLS050	A6T50	TJS50	JKS-50	JLS50	A4J50	JFL50
R5	035A-7	41	60	600	JJS-60	JLLS060	A6T60	TJS60	JKS-60	JLS60	A4T60	JFL60
R5	042A-7	52	80	600	JJS-80	JLLS080	A6T80	TJS80	JKS-80	JLS80	A4T80	JFL80
R5	049A-7	52	80	600	JJS-80	JLLS080	A6T80	TJS80	JKS-80	JLS80	A4T80	JFL80
R6	061A-7	62	110	600	JJS-110	JLLS110	A6T110	TJS110	JKS-110	JLS110	A4J110	JFL110
R6	084A-7	77	150	600	JJS-150	JLLS150	A6T150	TJS150	JKS-150	JLS150	A4J150	JFL150
R7	098A-7	99	150	600	JJS-150	JLLS150	A6T150	TJS150	JKS-150	JLS150	A4J150	JFL150
R7	119A-7	125	200	600	JJS-200	JLLS200	A6T200	TJS200	JKS-200	JLS200	A4J200	JFL200
R8	142A-7	144	250	600	JJS-250	JLLS250	A6T250	TJS250	JKS-250	JLS250	A4J250	JFL250
R8	174A-7	180	300	600	JJS-300	JLLS300	A6T300	TJS300	JKS-300	JLS300	A4J300	JFL300
R9	210A-7	242	400	600	JJS-400	JLLS400	A6T400	TJS400	UL Approval Pending			
R9	271A-7	271	400	600	JJS-400	JLLS400	A6T400	TJS400				

Frame Size	575 V ACS880-01-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 High Speed Class J Fuses				UL 248-4 Class CC Fast Acting Fuses				UL 248-17 Class CF Fast Acting Cube Fuse
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann
			A	V									
R3	07A4-7	7	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R3	09A9-7	9.4	20	600	DFJ-20	LDFJ020	HSJ20	JHL20	KTK-R-20	KLKR20	ATMR20	HCLR20	FCF20RN
R3	14A3-7	13.6	30	600	DFJ-30	LDFJ030	HSJ30	JHL30	KTK-R-30	KLKR30	ATMR30	HCLR30	FCF30RN
R3	019A-7	18	40	600	DFJ-40	LDFJ040	HSJ40	JHL40	-	-	-	-	FCF40RN
R3	023A-7	22	50	600	DFJ-50	LDFJ050	HSJ50	JHL50	-	-	-	-	FCF50RN
R3	027A-7	27	50	600	DFJ-50	LDFJ050	HSJ50	JHL50	-	-	-	-	FCF50RN
R5	035A-7	41	60	600	DFJ-60	LDFJ060	HSJ60	JHL60	-	-	-	-	FCF60RN
R5	042A-7	52	80	600	DFJ-80	LDFJ080	HSJ80	JHL80	-	-	-	-	FCF80RN
R5	049A-7	52	80	600	DFJ-80	LDFJ080	HSJ80	JHL80	-	-	-	-	FCF80RN
R6	061A-7	62	110	600	DFJ-110	LDFJ110	HSJ110	JHL110	-	-	-	-	-
R6	084A-7	77	150	600	DFJ-150	LDFJ150	HSJ150	JHL150	-	-	-	-	-
R7	098A-7	99	150	600	DFJ-150	LDFJ150	HSJ150	JHL150	-	-	-	-	-
R7	119A-7	125	200	600	DFJ-200	LDFJ200	HSJ200	JHL200	-	-	-	-	-
R8	142A-7	144	250	600	DFJ-250	LDFJ250	HSJ250	JHL250	-	-	-	-	-
R8	174A-7	180	300	600	DFJ-300	LDFJ300	HSJ300	JHL300	-	-	-	-	-
R9	210A-7	242	400	600	UL Approval Pending				-	-	-	-	-
R9	271A-7	271	400	600					-	-	-	-	-

3AXD10001032874.xls Rev C

**ACS880-04, 480 V fuses**

Frame Size	480 V ACS880-04-	Input Current	UL Fuse Size (A) and Voltage (V)		UL248-15 Class T Fast Acting Fuses				UL 248-10 Fast Acting Class L Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R10	460A-5	460	600	600	JJS-600	JLLS600	A6T600	TJS600	-	-	-	-
R10	503A-5	505	600	600	JJS-600	JLLS600	A6T600	TJS600	-	-	-	-
R10	583A-5	585	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
R10	635A-5	650	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
R11	715A-5	725	1000	600	-	JLLS1000	-	-	KTU-1000	LDC1000	A4BY1000	LCU1000
R11	820A-5	820	1000	600	-	JLLS1000	-	-	KTU-1000	LDC1000	A4BY1000	LCU1000
R11	880A-5	880	1000	600	-	JLLS1000	-	-	KTU-1000	LDC1000	A4BY1000	LCU1000

Frame Size	480 V ACS880-04-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 Fast Acting Class J Fuses				UL 248-8 High Speed Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R10	460A-5	460	600	600	JKS-600	JLS600	A4J600	JFL600	DFJ-600	LDJ600	HSJ600	JHL600
R10	503A-5	505	600	600	JKS-600	JLS600	A4J600	JFL600	DFJ-600	LDJ600	HSJ600	JHL600
R10	583A-5	585	800	600	-	-	-	-	-	-	-	-
R10	635A-5	650	800	600	-	-	-	-	-	-	-	-
R11	715A-5	725	1000	600	-	-	-	-	-	-	-	-
R11	820A-5	820	1000	600	-	-	-	-	-	-	-	-
R11	880A-5	880	1000	600	-	-	-	-	-	-	-	-

Frame Size	480 V ACS880-04-	Input Current	UL Fuse Size (A) and Voltage (V)		Bussmann Semiconductor Fuses UL 248-13 Recognized Fuses				
			Maximum Current	Voltage Rating	Type Flush End	Type DIN 43463	Type US Style	Type French Style	Type DIN 43620
			A	V					
R10	460A-5	460	630	690	170M6410	170M6010	170M6610	170M6310	170M6810D
R10	503A-5	505	700	690	170M6411	170M6011	170M6611	170M6311	170M6811D
R10	583A-5	585	700	690	170M6411	170M6011	170M6611	170M6311	170M6811D
R10	635A-5	650	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D
R11	715A-5	725	900	690	170M6413	170M6013	170M6613	170M6313	170M6813D
R11	820A-5	820	1000	690	170M6414	170M6014	170M6614	170M6314	170M6814D
R11	880A-5	880	1400	690	170M6417	170M6017	170M6617	170M6317	170M8555D

3AXD10001032874.xls Rev C

ACS880-04, 575 V fuses

Frame Size	575 V ACS880-04-	Input Current	UL Fuse Size (A) and Voltage (V)		UL248-15 Class T Fast Acting Fuses				UL 248-10 Fast Acting Class L Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison
			A	V								
R10	330A-7	330	500	600	JJS-500	JLLS500	A6T500	TJS500	-	-	-	-
R10	370A-7	370	500	600	JJS-500	JLLS500	A6T500	TJS500	-	-	-	-
R10	430A-7	430	500	600	JJS-500	JLLS500	A6T500	TJS500	-	-	-	-
R11	470A-7	470	600	600	JJS-600	JLLS600	A6T600	TJS600	-	-	-	-
R11	522A-7	522	600	600	JJS-600	JLLS600	A6T600	TJS600	-	-	-	-
R11	590A-7	590	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
R11	650A-7	650	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
R11	721A-7	721	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800

Frame Size	575 V ACS880-04-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 Fast Acting Class J Fuses				UL 248-8 High Speed Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/Ferraz		Bussmann	Littelfuse	Mersen/Ferraz Shawmut	Edison
			A	V								
R10	330A-7	330	500	600	JKS-500	JLS500	A4J500	JFL500	DFJ-500	LDJ500	HSJ500	JHL500
R10	370A-7	370	500	600	JKS-500	JLS500	A4J500	JFL500	DFJ-500	LDJ500	HSJ500	JHL500
R10	430A-7	430	500	600	JKS-500	JLS500	A4J500	JFL500	DFJ-500	LDJ500	HSJ500	JHL500
R11	470A-7	470	600	600	JKS-600	JLS600	A4J600	JFL600	DFJ-600	LDJ600	HSJ600	JHL600
R11	522A-7	522	600	600	JKS-600	JLS600	A4J600	JFL600	DFJ-600	LDJ600	HSJ600	JHL600
R11	590A-7	590	800	600	-	-	-	-	-	-	-	-
R11	650A-7	650	800	600	-	-	-	-	-	-	-	-
R11	721A-7	721	800	600	-	-	-	-	-	-	-	-

Frame Size	575 V ACS880-04-	Input Current	UL Fuse Size (A) and Voltage (V)		Bussmann Semiconductor Fuses UL 248-13 Recognized Fuses				
			Maximum Current	Voltage Rating	Type Flush End	Type DIN 43463	Type US Style	Type French Style	Type DIN 43620
			A	V					
R10	330A-7	330	630	690	170M6410	170M6010	170M6610	170M6310	170M6810D
R10	370A-7	370	630	690	170M6410	170M6010	170M6610	170M6310	170M6810D
R10	430A-7	430	700	690	170M6411	170M6011	170M6611	170M6311	170M6811D
R11	470A-7	470	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D
R11	522A-7	522	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D
R11	590A-7	590	900	690	170M6413	170M6013	170M6613	170M6313	170M6813D
R11	650A-7	650	1000	690	170M6414	170M6014	170M6614	170M6314	170M6814D
R11	721A-7	721	1250	600	170M6416	170M6016	170M6616	170M6316	170M8554D

3AXD10001032874.xls Rev C



**ACS880-04XT, 480 V fuses**

Frame Size	480 V ACS880-04XT-	Input Current	UL Fuse Size (A) and Voltage (V)		UL248-15 Class T Fast Acting Fuses				UL 248-10 Fast Acting Class L Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
(2) R10	1010A-5	1010	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
(2) R10	1160A-5	1160	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
(2) R11	1310A-5	1310	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
(2) R11	1610A-5	1610	1000	600	-	JLLS1000	-	-	KTU-1000	LDC1000	A4BY1000	LCU1000

Frame Size	480 V ACS880-04XT-	Input Current	UL Fuse Size (A) and Voltage (V)		Bussmann Semiconductor Fuses UL 248-13 Recognized Fuses				
			Maximum Current	Voltage Rating	Type Flush End	Type DIN 43463	Type US Style	Type French Style	Type DIN 43620
			A	V					
(2) R10	1010A-5	1010	700	690	170M6411	170M6011	170M6611	170M6311	170M6811D
(2) R10	1160A-5	1160	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D
(2) R11	1310A-5	1310	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D
(2) R11	1610A-5	1610	1000	690	170M6414	170M6014	170M6614	170M6314	170M6814D

Six fuses required per installation

**ACS880-04XT, 575 V fuses**

Frame Size	575 V ACS880-04XT-	Input Current	UL Fuse Size (A) and Voltage (V)		UL248-15 Class T Fast Acting Fuses				UL 248-10 Fast Acting Class L Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
(2) R10	0810A-7	810	500	600	JJS-500	JLLS500	A6T500	TJS500	-	-	-	-
(2) R11	0960A-7	960	600	600	JJS-600	JLLS600	A6T600	TJS600	-	-	-	-
(2) R11	1080A-7	1080	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
(2) R11	1320A-7	1320	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800

Frame Size	575 V ACS880-04XT-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 Fast Acting Class J Fuses				UL 248-8 High Speed Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
(2) R10	0810A-7	810	500	600	JKS-500	JLS500	A4J500	JFL500	DFJ-500	LDJ500	HSJ500	JHL500
(2) R11	0960A-7	960	600	600	JKS-600	JLS600	A4J600	JFL600	DFJ-600	LDJ600	HSJ600	JHL600
(2) R11	1080A-7	1080	800	600	-	-	-	-	-	-	-	-
(2) R11	1320A-7	1320	800	600	-	-	-	-	-	-	-	-

Frame Size	575 V ACS880-04XT-	Input Current	UL Fuse Size (A) and Voltage (V)		Bussmann Semiconductor Fuses UL 248-13 Recognized Fuses				
			Maximum Current	Voltage Rating	Type Flush End	Type DIN 43463	Type US Style	Type French Style	Type DIN 43620
			A	V					
(2) R10	0810A-7	810	630	690	170M6410	170M6010	170M6610	170M6310	170M6810D
(2) R11	0960A-7	960	630	690	170M6410	170M6010	170M6610	170M6310	170M6810D
(2) R11	1080A-7	1080	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D
(2) R11	1320A-7	1320	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D

Six fuses required per installation  
(2) = two modules per drive

3AXD10001032874.xls Rev C

**ACS880-04F, 480 V fuses**

Frame Size	480 V ACS880-04F-	Input Current	UL Fuse Size (A) and Voltage (V)		UL248-15 Class T Fast Acting Fuses				UL 248-10 Fast Acting Class L Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R10	459A-5	459	600	600	JJS-600	JLLS600	A6T600	TJS600	-	-	-	-
R10	502A-5	502	600	600	JJS-600	JLLS600	A6T600	TJS600	-	-	-	-
R10	582A-5	582	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
R10	634A-5	634	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
R11	715A-5	715	1000	600	-	JLLS1000	-	-	KTU-1000	LDC1000	A4BY1000	LCU1000
R11	820A-5	820	1000	600	-	JLLS1000	-	-	KTU-1000	LDC1000	A4BY1000	LCU1000
R11	880A-5	880	1000	600	-	JLLS1000	-	-	KTU-1000	LDC1000	A4BY1000	LCU1000

Frame Size	480 V ACS880-04F-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 Fast Acting Class J Fuses				UL 248-8 High Speed Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R10	459A-5	459	600	600	JKS-600	JLS600	A4J600	JFL600	DFJ-600	LDFJ600	HSJ600	JHL600
R10	502A-5	502	600	600	JKS-600	JLS600	A4J600	JFL600	DFJ-600	LDFJ600	HSJ600	JHL600
R10	582A-5	582	800	600	-	-	-	-	-	-	-	-
R10	634A-5	634	800	600	-	-	-	-	-	-	-	-
R11	715A-5	715	1000	600	-	-	-	-	-	-	-	-
R11	820A-5	820	1000	600	-	-	-	-	-	-	-	-
R11	880A-5	880	1000	600	-	-	-	-	-	-	-	-

Frame Size	480 V ACS880-04F-	Input Current	UL Fuse Size (A) and Voltage (V)		Bussmann Semiconductor Fuses UL 248-13 Recognized Fuses				
			Maximum Current	Voltage Rating	Type Flush End	Type DIN 43463	Type US Style	Type French Style	Type DIN 43620
			A	V					
R10	459A-5	459	630	690	170M6410	170M6010	170M6610	170M6310	170M6810D
R10	502A-5	502	700	690	170M6411	170M6011	170M6611	170M6311	170M6811D
R10	582A-5	582	700	690	170M6411	170M6011	170M6611	170M6311	170M6811D
R10	634A-5	634	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D
R11	715A-5	715	900	690	170M6413	170M6013	170M6613	170M6313	170M6813D
R11	820A-5	820	1000	690	170M6414	170M6014	170M6614	170M6314	170M6814D
R11	880A-5	880	1400	690	170M6417	170M6017	170M6617	170M6317	170M8555D

3AXD10001032874.xls Rev C

**ACS880-04F, 575 V fuses**

Frame Size	575 V ACS880-04F-	Input Current	UL Fuse Size (A) and Voltage (V)		UL248-15 Class T Fast Acting Fuses				UL 248-10 Fast Acting Class L Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R10	329A-7	329	500	600	JJS-500	JLLS500	A6T500	TJS500	-	-	-	-
R10	369A-7	369	500	500	JJS-500	JLLS500	A6T500	TJS500	-	-	-	-
R10	429A-7	429	500	500	JJS-500	JLLS500	A6T500	TJS500	-	-	-	-
R11	470A-7	470	600	600	JJS-600	JLLS600	A6T600	TJS600	-	-	-	-
R11	522A-7	522	600	600	JJS-600	JLLS600	A6T600	TJS600	-	-	-	-
R11	590A-7	590	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
R11	650A-7	650	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
R11	721A-7	721	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800

Frame Size	575 V ACS880-04F-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 Fast Acting Class J Fuses				UL 248-8 High Speed Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R10	329A-7	329	500	600	JKS-500	JLS500	A4J500	JFL500	DFJ-500	LDJ500	HSJ500	JHL500
R10	369A-7	369	500	500	JKS-500	JLS500	A4J500	JFL500	DFJ-500	LDJ500	HSJ500	JHL500
R10	429A-7	429	500	500	JKS-500	JLS500	A4J500	JFL500	DFJ-500	LDJ500	HSJ500	JHL500
R11	470A-7	470	600	600	JKS-600	JLS600	A4J600	JFL600	DFJ-600	LDJ600	HSJ600	JHL600
R11	522A-7	522	600	600	JKS-600	JLS600	A4J600	JFL600	DFJ-600	LDJ600	HSJ600	JHL600
R11	590A-7	590	800	600	-	-	-	-	-	-	-	-
R11	650A-7	650	800	600	-	-	-	-	-	-	-	-
R11	721A-7	721	800	600	-	-	-	-	-	-	-	-

Frame Size	575 V ACS880-04F-	Input Current	UL Fuse Size (A) and Voltage (V)		Bussmann Semiconductor Fuses UL 248-13 Recognized Fuses				
			Maximum Current	Voltage Rating	Type Flush End	Type DIN 43463	Type US Style	Type French Style	Type DIN 43620
			A	V					
R10	329A-7	329	630	690	170M6410	170M6010	170M6610	170M6310	170M6810D
R10	369A-7	369	630	690	170M6410	170M6010	170M6610	170M6310	170M6810D
R10	429A-7	429	700	690	170M6411	170M6011	170M6611	170M6311	170M6811D
R11	470A-7	470	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D
R11	522A-7	522	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D
R11	590A-7	590	900	690	170M6413	170M6013	170M6613	170M6313	170M6813D
R11	650A-7	650	1000	690	170M6414	170M6014	170M6614	170M6314	170M6814D
R11	721A-7	721	1250	690	170M6416	170M6016	170M6616	170M6316	170M8554D

3AXD10001032874.xls Rev C

**ACS880-04FXT, 480 V fuses**

Frame Size	480 V ACS880-04FXT-	Input Current	UL Fuse Size (A) and Voltage (V)		UL248-15 Class T Fast Acting Fuses				UL 248-10 Fast Acting Class L Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	A	V							
(2) R10	1008A-5	1008	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
(2) R10	1158A-5	1158	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
(2) R11	1310A-5	1310	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
(2) R11	1610A-5	1610	1000	600	-	JLLS1000	-	-	KTU-1000	LDC1000	A4BY1000	LCU1000

Frame Size	480 V ACS880-04FXT-	Input Current	UL Fuse Size (A) and Voltage (V)		Bussmann Semiconductor Fuses UL 248-13 Recognized Fuses				
			Maximum Current	Voltage Rating	Type Flush End	Type DIN 43463	Type US Style	Type French Style	Type DIN 43620
			A	A	V				
(2) R10	1008A-5	1008	700	690	170M6411	170M6011	170M6611	170M6311	170M6811D
(2) R10	1158A-5	1158	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D
(2) R11	1310A-5	1310	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D
(2) R11	1610A-5	1610	1000	690	170M6414	170M6014	170M6614	170M6314	170M6814D

Six fuses required per installation  
(2) = two modules per drive

**ACS880-04FXT, 575 V fuses**

Frame Size	575 V ACS880-04FXT-	Input Current	UL Fuse Size (A) and Voltage (V)		UL248-15 Class T Fast Acting Fuses				UL 248-10 Fast Acting Class L Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	A	V							
(2) R10	0808A-7	808	500	600	JJS-500	JLLS500	A6T500	TJS500	-	-	-	-
(2) R11	0960A-7	960	600	600	JJS-600	JLLS600	A6T600	TJS600	-	-	-	-
(2) R11	1080A-7	1080	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800
(2) R11	1320A-7	1320	800	600	JJS-800	JLLS800	A6T800	TJS800	KTU-800	LDC800	A4BY800	LCU800

Frame Size	575 V ACS880-04FXT-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 Fast Acting Class J Fuses				UL 248-8 High Speed Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	A	V							
(2) R10	0808A-7	808	500	600	JKS-500	JLS500	A4J500	JFL500	DFJ-500	LDJ500	HSJ500	JHL500
(2) R11	0960A-7	960	600	600	JKS-600	JLS600	A4J600	JFL600	DFJ-600	LDJ600	HSJ600	JHL600
(2) R11	1080A-7	1080	800	600	-	-	-	-	-	-	-	-
(2) R11	1320A-7	1320	800	600	-	-	-	-	-	-	-	-

Frame Size	575 V ACS880-04FXT-	Input Current	UL Fuse Size (A) and Voltage (V)		Bussmann Semiconductor Fuses UL 248-13 Recognized Fuses				
			Maximum Current	Voltage Rating	Type Flush End	Type DIN 43463	Type US Style	Type French Style	Type DIN 43620
			A	A	V				
(2) R10	0808A-7	808	630	690	170M6410	170M6010	170M6610	170M6310	170M6810D
(2) R11	0960A-7	960	630	690	170M6410	170M6010	170M6610	170M6310	170M6810D
(2) R11	1080A-7	1080	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D
(2) R11	1320A-7	1320	800	690	170M6412	170M6012	170M6612	170M6312	170M6812D

Six fuses required per installation  
(2) = two modules per drive

3AXD10001032874.xls Rev C

**ACS880-11, -31, 480 V fuses**

Frame Size	480 V ACS880-11- ACS880-31-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-15 Class T Fast Acting Fuses				UL 248-8 Fast Acting Class J Fuses			
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison
			A	V								
R3	07A6-5	5.8	15	600	JJS-15	JLLS015	A6T15	TJS15	JKS-15	JLS15	A4J15	JFL15
R3	11A0-5	7.8	20	600	JJS-20	JLLS020	A6T20	TJS20	JKS-20	JLS20	A4J20	JFL20
R3	014A-5	10.6	25	600	JJS-25	JLLS025	A6T25	TJS25	JKS-25	JLS25	A4J25	JFL25
R3	021A-5	15.6	35	600	JJS-35	JLLS035	A6T35	TJS35	JKS-35	JLS35	A4J35	JFL35
R6	027A-5	21.3	40	600	JJS-40	JLLS040	A6T40	TJS40	JKS-40	JLS40	A4J40	JFL40
R6	034A-5	26.2	50	600	JJS-50	JLLS050	A6T50	TJS50	JKS-50	JLS50	A4J50	JFL50
R6	040A-5	31.2	60	600	JJS-60	JLLS060	A6T60	TJS60	JKS-60	JLS60	A4J60	JFL60
R6	052A-5	40.1	80	600	JJS-80	JLLS080	A6T80	TJS80	JKS-80	JLS80	A4J80	JFL80
R6	065A-5	49.5	90	600	JJS-90	JLLS090	A6T90	TJS90	JKS-90	JLS90	A4J90	JFL90
R6	077A-5	60.2	110	600	JJS-110	JLLS110	A6T110	TJS110	JKS-110	JLS110	A4J110	JFL110
R8	101A-5	74	150	600	JJS-150	JLLS150	A6T150	TJS150	JKS-150	JLS150	A4J150	JFL150
R8	124A-5	100	200	600	JJS-200	JLLS200	A6T200	TJS200	JKS-200	JLS200	A4J200	JFL200
R8	156A-5	120	225	600	JJS-225	JLLS225	A6T225	TJS225	JKS-225	JLS225	A4J225	JFL225
R8	180A-5	147	300	600	JJS-300	JLLS300	A6T300	TJS300	JKS-300	JLS300	A4T300	JFL300

Frame Size	480 V ACS880-11- ACS880-31-	Input Current	UL Fuse Size (A) and Voltage (V)		UL 248-8 High Speed Class J Fuses				UL 248-4 Class CC Fast Acting Fuses				UL 248-17 Class CF Fast Acting Cube Fuse
			Maximum Current	Voltage Rating	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann	Littelfuse	Mersen/ Ferraz Shawmut	Edison	Bussmann
			A	V									
R3	07A6-5	5.8	15	600	DFJ-15	LDFJ015	HSJ15	JHL15	KTK-R-15	KLKR15	ATMR15	HCLR15	FCF15RN
R3	11A0-5	7.8	20	600	DFJ-20	LDFJ020	HSJ20	JHL20	KTK-R-20	KLKR20	ATMR20	HCLR20	FCF20RN
R3	014A-5	10.6	25	600	DFJ-25	LDFJ025	HSJ25	JHL25	KTK-R-25	KLKR25	ATMR25	HCLR25	FCF25RN
R3	021A-5	15.6	35	600	DFJ-35	LDFJ035	HSJ35	JHL35	-	-	-	-	FCF35RN
R6	027A-5	21.3	40	600	DFJ-40	LDFJ040	HSJ40	JHL40	-	-	-	-	FCF40RN
R6	034A-5	26.2	50	600	DFJ-50	LDFJ050	HSJ50	JHL50	-	-	-	-	FCF50RN
R6	040A-5	31.2	60	600	DFJ-60	LDFJ060	HSJ60	JHL60	-	-	-	-	FCF60RN
R6	052A-5	40.1	80	600	DFJ-80	LDFJ080	HSJ80	JHL80	-	-	-	-	FCF80RN
R6	065A-5	49.5	90	600	DFJ-90	LDFJ090	HSJ90	JHL90	-	-	-	-	FCF90RN
R6	077A-5	60.2	110	600	DFJ-110	LDFJ110	HSJ110	JHL110	-	-	-	-	-
R8	101A-5	74	150	600	DFJ-150	LDFJ150	HSJ150	JHL150	-	-	-	-	-
R8	124A-5	100	200	600	DFJ-200	LDFJ200	HSJ200	JHL200	-	-	-	-	-
R8	156A-5	120	225	600	DFJ-225	LDFJ225	HSJ225	JHL225	-	-	-	-	-
R8	180A-5	147	300	600	DFJ-300	LDFJ300	HSJ300	JHL300	-	-	-	-	-

3AXD10001032874.xls Rev C

**ACS880-14, -34, 480 V fuses**

Frame Size	480 V ACS880-14- ACS880-34-	Input Current	UL Fuse Size (A) and Voltage (V)		Bussmann Semiconductor Fuses UL 248-13 Recognized Fuses			
			Maximum Current	Voltage Rating	Type Flush End	Type DIN 43463	Type US Style	Type French Style
		A	A	V				
R11	240A-5	169	315	690	170M4410	170M4010	170M4610	170M4310
R11	260A-5	205	400	690	170M5408	170M5008	170M5608	170M5308
R11	302A-5	239	500	690	170M5410	170M5010	170M5610	170M5310
R11	361A-5	257	630	690	170M6410	170M6010	170M6610	170M6310
R11	414A-5	321	700	690	170M6411	170M6011	170M6611	170M6311
R11	460A-5	404	700	690	170M6411	170M6011	170M6611	170M6311
R11	503A-5	455	800	690	170M6412	170M6012	170M6612	170M6312

**ACS880-14, -34, 575 V fuses**

Frame Size	575 V ACS880-14- ACS880-34-	Input Current	UL Fuse Size (A) and Voltage (V)		Bussmann Semiconductor Fuses UL 248-13 Recognized Fuses			
			Maximum Current	Voltage Rating	Type Flush End	Type DIN 43463	Type US Style	Type French Style
		A	A	V				
R11	142A-7	125	250	690	170M4409	170M4009	170M4609	170M4309
R11	174A-7	146	315	690	170M4410	170M4010	170M4610	170M4310
R11	210A-7	166	400	690	170M5408	170M5008	170M5608	170M5308
R11	271A-7	208	500	690	170M5410	170M5010	170M5610	170M5310
R11	330A-7	250	630	690	170M6410	170M6010	170M6610	170M6310
R11	370A-7	291	700	690	170M6411	170M6011	170M6611	170M6311
R11	430A-7	375	700	690	170M6411	170M6011	170M6611	170M6311

3AXD10001032874.xls Rev C

## Circuit Breaker Information

ACS880-01 drives are suitable for use on a circuit capable of delivering not more than 65 kA symmetrical amperes (RMS) at 480 V maximum, when protected by appropriate circuit breakers. See note regarding UL508A Industrial control panels and alternate current limiting fuses at end of the document.

ACS880-01 units are tested with ABB current limiting inverse time circuit breakers rated at 65kA and 480V. When using circuit breakers at 480V the following rules must be followed:


1. When designing UL508A panels, Article SB 4.2.3 Exception No. 3 allows use of other manufacturers' current limiting inverse time circuit breakers which have same voltage, current and interrupting rating, if  $I_{peak}$  and  $I^2t$  are the same or less than the ABB specified circuit breaker.
2. Non-current limiting inverse time circuit breakers must not be used.
3. Drive must be mounted in an enclosure  $\geq$  Enclosure Minimum Volume listed in the table below.
4. Enclosures for ACS880-01 480V frames R1 and R9 must have a solid bottom directly below the drive. i.e. fans, filters or louvers cannot be mounted directly below the drive but can be mounted in adjacent areas on the bottom of the enclosure.
5. When multiple drives are installed in the same enclosure, minimum volume of the enclosure is determined by largest Enclosure Minimum Volume of the drives to be placed in the enclosure, plus the volume(s) of each additional drive. i.e. for R6 and R3 drive select enclosure with the volume  $\geq 53703+991 = 54694 \text{ in}^3$ .
6. Open Type, Type 1 and Type 12 drives can be used inside of the enclosure. Use drive volume for all three types listed in the table when installing multiple drives in the panel.
7. ABB circuit breaker part number listed in table is a base part number. Last eight characters of the breaker "FF000XXX" represent optional accessories which can be added to the breaker. These accessories have no impact on the performance or rating of the breakers.

## ACS880-01, 480 V circuit breakers

Frame Size	480 V ACS880-01-	Input Current (A)	CB Nominal Current (A)	CB Voltage (V)	Enclosure Minimum Volume (in <sup>3</sup> )	Drive Volume (in <sup>3</sup> )	Circuit Breaker (ABB) 65kA @ 480 V	Circuit Breaker (Rockwell) 65kA @ 480 V	Maximum I <sup>2</sup> t (A <sup>2</sup> s)	Maximum Ipeak (kA)
R1	02A1-5	2.1	15	480	8100	459	XT2HU3015AFF000XXX	140G-HC6C3-C15	0.512x10 <sup>6</sup>	23.2
R1	03A0-5	3.0	15	480	8100	459	XT2HU3015AFF000XXX	140G-HC6C3-C15	0.512x10 <sup>6</sup>	23.2
R1	03A4-5	3.4	15	480	8100	459	XT2HU3015AFF000XXX	140G-HC6C3-C15	0.512x10 <sup>6</sup>	23.2
R1	04A8-5	4.8	15	480	8100	459	XT2HU3015AFF000XXX	140G-HC6C3-C15	0.512x10 <sup>6</sup>	23.2
R1	05A2-5	5.2	15	480	8100	459	XT2HU3015AFF000XXX	140G-HC6C3-C15	0.512x10 <sup>6</sup>	23.2
R1	07A6-5	7.6	15	480	8100	459	XT2HU3015AFF000XXX	140G-HC6C3-C15	0.512x10 <sup>6</sup>	23.2
R1	11A0-5	11	15	480	8100	459	XT2HU3015AFF000XXX	140G-HC6C3-C15	0.512x10 <sup>6</sup>	23.2
R2	014A-5	14	30	480	27720	539	XT2HU3030AFF000XXX	140G-HC6C3-C30	0.512x10 <sup>6</sup>	23.2
R2	021A-5	21	30	480	27720	539	XT2HU3030AFF000XXX	140G-HC6C3-C30	0.512x10 <sup>6</sup>	23.2
R3	027A-5	27	50	480	27720	737	XT2HU3050AFF000XXX	140G-HC6C3-C50	0.512x10 <sup>6</sup>	23.2
R3	034A-5	34	50	480	27720	737	XT2HU3050AFF000XXX	140G-HC6C3-C50	0.512x10 <sup>6</sup>	23.2
R4	040A-5	40	70	480	30240	1232	XT2HU3070AFF000XXX	140G-HC6C3-C70	0.512x10 <sup>6</sup>	23.2
R4	052A-5	52	70	480	30240	1232	XT2HU3070AFF000XXX	140G-HC6C3-C70	0.512x10 <sup>6</sup>	23.2
R5	065A-5	65	125	480	30240	1466	XT2HU3125EFF000XXX	140G-HC6H3-D12	0.98x10 <sup>6</sup>	30
R5	077A-5	77	125	480	30240	1466	XT2HU3125EFF000XXX	140G-HC6H3-D12	0.98x10 <sup>6</sup>	30
R6	096A-5	96	225	480	53703	2365	XT4HU3225EFF000XXX	140G-JC6H3-D25	0.98x10 <sup>6</sup>	30
R6	124A-5	124	225	480	53703	2365	XT4HU3225EFF000XXX	140G-JC6H3-D25	0.98x10 <sup>6</sup>	30
R7	156A-5	156	250	480	53703	2948	XT4HU3250EFF000XXX	140G-JC6H3-D25	0.98x10 <sup>6</sup>	30
R7	180A-5	180	250	480	53703	2948	XT4HU3250EFF000XXX	140G-JC6H3-D25	0.98x10 <sup>6</sup>	30
R8	240A-5	240	400	480	53703	3858	XT5HU340AEFF000XXX	140G-KC6H3-D40	4.2x10 <sup>6</sup>	47.9
R8	260A-5	260	400	480	53703	3858	XT5HU340AEFF000XXX	140G-KC6H3-D40	4.2x10 <sup>6</sup>	47.9
R9	302A-5	302	400	480						
R9	361A-5	361	500	480						
R9	414A-5	414	600	480						

UL Approval Pending

3AXD10001032874.xls Rev C



3AXD50000645015C